


MOTOROLA
SEMICONDUCTOR
TECHNICAL DATA
The RF Line
**60-Channel (450 MHz) CATV
Line Extender Amplifier**

... designed for broadband applications requiring low-distortion amplification. Specifically intended for CATV market requirements. This amplifier features ion-implanted arsenic emitter transistors and an all gold metallization system.

- Specified Characteristics at $V_{CC} = 24\text{ V}$, $T_C = 25^\circ\text{C}$:
 - Frequency Range — 40 to 450 MHz
 - Power Gain — 34 dB Typ @ $f = 50\text{ MHz}$
 - Noise Figure — 6 dB Max @ $f = 450\text{ MHz}$
 - CTB — -58 dB Max @ $V_{out} = 46\text{ dBmV}$
- All Gold Metallization for Improved Reliability
- Superior Gain, Return Loss and DC Current Stability with Temperature

CA5600

 34 dB
 40-450 MHz
 60-CHANNEL CATV
 LINE EXTENDER
 AMPLIFIER

 CA
 CASE 714F-01, STYLE 1

MAXIMUM RATINGS

Rating	Symbol	Value	Unit
RF Voltage Input (Single Tone)	V_{in}	+50	dBmV
DC Supply Voltage	V_{CC}	28	Vdc
Operating Case Temperature Range	T_C	-20 to +100	$^\circ\text{C}$
Storage Temperature Range	T_{stg}	-40 to +100	$^\circ\text{C}$

ELECTRICAL CHARACTERISTICS ($V_{CC} = 24\text{ V}$, $T_C = 25^\circ\text{C}$, 75 Ω system unless otherwise noted)

Characteristic	Symbol	Min	Typ	Max	Unit
Frequency Range	BW	40	—	450	MHz
Power Gain — 50 MHz	G_P	33	34	35	dB
Slope	S	+0.5	—	+2	dB
Gain Flatness	—	—	—	± 0.4	dB
Return Loss — Input/Output ($f = 40\text{--}450\text{ MHz}$)	IRL/ORL	18	—	—	dB
Second Order Intermodulation Distortion ($V_{out} = +50\text{ dBmV}$ per ch., ch. 2, H5, H14)	IMD	—	—	-64	dB
Cross Modulation Distortion ($V_{out} = +46\text{ dBmV}$ per ch., ch. 2, 60-channel flat)	XMD_{60}	—	—	-58	dB
Composite Triple Beat ($V_{out} = +46\text{ dBmV}$ per ch., ch. H22, 60-channel flat)	CTB_{60}	—	—	-58	dB
Noise Figure ($f = 50\text{ MHz}$) ($f = 450\text{ MHz}$)	NF	—	—	4.5 6	dB
DC Current	I_{DC}	—	310	—	mA