TetraFET

D1218UK

METAL GATE RF SILICON FET

MECHANICAL DATA



DD

PIN 1	SOURCE (COMMON)	PIN 2	DRAIN 1
PIN 3	DRAIN 2	PIN 4	SOURCE (COMMON)
PIN 5	SOURCE (COMMON)	PIN 6	GATE 2
PIN 7	GATE 1	PIN 8	SOURCE (COMMON)

DIM	mm	Tol.	Inches	Tol.
A	9.14	0.13	0.360	0.005
B	12.70	0.13	0.500	0.005
C	45°	5°	45°	5°
D	6.86	0.13	0.270	0.005
E	0.76	0.13	0.030	0.005
F	9.78	0.13	0.385	0.005
G	19.05	0.25	0.750	0.010
H	4.19	0.13	0.165	0.005
I	3.17	0.13	0.125	0.005
J	1.52R	0.13	0.060R	0.005
K	1.65R	0.13	0.065R	0.005
M	16.51	0.13	0.650	0.005
N	22.86	0.13	0.900	0.005
O	0.13	0.02	0.005	0.001
P	6.35	0.64	0.250	0.025
Q	10.77	0.13	0.424	0.005

GOLD METALLISED MULTI-PURPOSE SILICON DMOS RF FET 60W – 12.5V – 500MHz PUSH–PULL

FEATURES

- **SIMPLIFIED AMPLIFIER DESIGN**
- **SUITABLE FOR BROAD BAND APPLICATIONS**
- **LOW C_{rss}**
- **SIMPLE BIAS CIRCUITS**
- **LOW NOISE**
- **HIGH GAIN – 10 dB MINIMUM**

APPLICATIONS

- HF/VHF/UHF COMMUNICATIONS from 1 MHz to 500 MHz

ABSOLUTE MAXIMUM RATINGS (T_{case} = 25°C unless otherwise stated)

P_D	Power Dissipation	290W
BV_{DSS}	Drain – Source Breakdown Voltage *	40V
BV_{GSS}	Gate – Source Breakdown Voltage *	±20V
$I_{D(sat)}$	Drain Current*	30A
T_{stg}	Storage Temperature	–65 to 150°C
T_j	Maximum Operating Junction Temperature	200°C

* Per Side

Semelab Plc reserves the right to change test conditions, parameter limits and package dimensions without notice. Information furnished by Semelab is believed to be both accurate and reliable at the time of going to press. However Semelab assumes no responsibility for any errors or omissions discovered in its use. Semelab encourages customers to verify that datasheets are current before placing orders.

Semelab plc. Telephone +44(0)1455 556565. Fax +44(0)1455 552612.
E-mail: sales@semelab.co.uk Website: http://www.semelab.co.uk

Document Number 3175
Issue 1

ELECTRICAL CHARACTERISTICS (T_{case} = 25°C unless otherwise stated)

Parameter		Test Conditions		Min.	Typ.	Max.	Unit
PER SIDE							
BV_{DSS}	Drain–Source Breakdown Voltage	V_{GS} = 0	I_D = 100mA	40			V
I_{DSS}	Zero Gate Voltage Drain Current	V_{DS} = 12.5V	V_{GS} = 0			1	mA
I_{GSS}	Gate Leakage Current	V_{GS} = 20V	V_{DS} = 0			1	µA
$V_{GS(th)}$	Gate Threshold Voltage*	I_D = 10mA	V_{DS} = V_{GS}	1		7	V
g_{fs}	Forward Transconductance*	V_{DS} = 10V	I_D = 3A	2.4			mhos
TOTAL DEVICE							
G_{PS}	Common Source Power Gain	P_O = 60W		10			dB
η	Drain Efficiency	V_{DS} = 12.5V	I_{DQ} = 2.4A	50			%
VSWR	Load Mismatch Tolerance	f = 500MHz		20:1			—
PER SIDE							
C_{iss}	Input Capacitance	V_{DS} = 0V	V_{GS} = –5V f = 1MHz			180	pF
C_{oss}	Output Capacitance	V_{DS} = 12.5V	V_{GS} = 0 f = 1MHz			120	pF
C_{rss}	Reverse Transfer Capacitance	V_{DS} = 12.5V	V_{GS} = 0 f = 1MHz			12	pF

* Pulse Test: Pulse Duration = 300 µs , Duty Cycle ≤ 2%

HAZARDOUS MATERIAL WARNING

The ceramic portion of the device between leads and metal flange is beryllium oxide. Beryllium oxide dust is highly toxic and care must be taken during handling and mounting to avoid damage to this area.

THESE DEVICES MUST NEVER BE THROWN AWAY WITH GENERAL INDUSTRIAL OR DOMESTIC WASTE.

THERMAL DATA

$R_{THj–case}$	Thermal Resistance Junction – Case	Max. 0.6°C / W

Semelab Plc reserves the right to change test conditions, parameter limits and package dimensions without notice. Information furnished by Semelab is believed to be both accurate and reliable at the time of going to press. However Semelab assumes no responsibility for any errors or omissions discovered in its use. Semelab encourages customers to verify that datasheets are current before placing orders.

Semelab plc. Telephone +44(0)1455 556565. Fax +44(0)1455 552612.
E-mail: sales@semelab.co.uk Website: http://www.semelab.co.uk