

Features

- High-performance laser diode driver
- Voltage-controlled output current source to 150 mA per channel, requiring one external set resistor per channel
- Current-controlled output current source to 150 mA per channel
- Rise time = 1.0 ns
- Fall time = 1.1 ns
- On chip oscillator with frequency and amplitude control by use of external resistors to ground
- Oscillator to 500 MHz
- Oscillator to 100 mA pk/pk
- Single +5V supply ($\pm 10\%$)
- Current amplification = 100
- Disable feature for power-up protection and power savings
- TTL/CMOS control signals
- Fast Settling APC Amplifier

Applications

- DVD drives
- CD-RW applications
- Writable optical drives
- Laser diode current switching

Ordering Information

Part No	Temp. Range	Package	Outline #
EL6258CU	0°C to +70°C	QSOP-24	MDP0040

General Description


The EL6258C is a high-performance three channel laser diode current amplifier that provides controlled current to a grounded laser diode. The three amplifiers can provide up to 150 mA per channel of DC or pulsed current. Channels 2 and 3 must be used as the write channels, with switching speeds of approximately one nanosecond rise/fall time. All three channels are summed together at the I_{OUT} output, allowing the user to create multilevel waveforms. Each level of output current is set by an analog voltage applied to an external resistor which converts the voltage into a current at the I_{IN} pins (virtually ground). The current seen at these pins is then amplified by 100X (150X on CH3) to become a current source at pin I_{OUT}.

An on-chip 500 MHz oscillator is provided to allow current modulation when in the read mode. This is turned on when the OSCEN pin is held high (floating not recommended). Complete control of amplitude and frequency is set by two external resistors connected to ground at pins RFREQ and RAMP (see graphs in this data sheet for further explanation). The oscillator will also turn off whenever either of the OUTEN pins for channels 2 or 3 (the write channels) are low (see truth table).

Output current pulses are enabled when an 'L' signal is applied to the OUTEN pins. No output current flows when OUTEN is 'H', and additional laser diode protection is provided since the OUTEN input will float high when open. Complete I_{OUT} shut-off is also achieved by holding the ENABLE pin low, which will override the OUTEN control pins.

The EL6258C also includes a fast settling APC amplifier designed to interface directly with the power monitor photodiode and the sample-and-hold amplifier, for read and write power control.

Connection Diagram



EL6258C - Product Brief

3-Channel Laser Driver + Oscillator + APC Amplifier

General Disclaimer

Specifications contained in this data sheet are in effect as of the publication date shown. Elantec, Inc. reserves the right to make changes in the circuitry or specifications contained herein at any time without notice. Elantec, Inc. assumes no responsibility for the use of any circuits described herein and makes no representations that they are free from patent infringement.

élantec

HIGH PERFORMANCE ANALOG INTEGRATED CIRCUITS

Elantec, Inc.

675 Trade Zone Blvd.

Milpitas, CA 95035

Telephone: (408) 945-1323

(888) 352-6832 (toll free)

Fax: (408) 945-9305

European Office: 44-18-977-6020

WARNING - Life Support Policy

Elantec, Inc. products are not authorized for and should not be used within Life Support Systems without the specific written consent of Elantec, Inc. Life Support systems are equipment intended to support or sustain life and whose failure to perform when properly used in accordance with instructions provided can be reasonably expected to result in significant personal injury or death. Users contemplating application of Elantec, Inc. Products in Life Support Systems are requested to contact Elantec, Inc. factory headquarters to establish suitable terms & conditions for these applications. Elantec, Inc.'s warranty is limited to replacement of defective components and does not cover injury to persons or property or other consequential damages.