

LM317M

3-TERMINAL ADJUSTABLE REGULATOR

SLVS297C – APRIL 2000 – REVISED NOVEMBER 2001

- Output Voltage Range Adjustable From 1.2 V to 37 V
- Output Current Greater Than 500 mA
- Internal Short-Circuit Current Limiting
- Thermal Overload Protection
- Output Safe-Area Compensation


description

The LM317M is an adjustable 3-terminal positive-voltage regulator capable of supplying more than 500 mA over an output-voltage range of 1.2 V to 37 V. The LM317M is exceptionally easy to use and requires only two external resistors to set the output voltage. Furthermore, both line and load regulation are better than standard fixed regulators. The LM317M is packaged in the DPAK/TO-252-equivalent KTP package, which is easy to handle and use.

In addition to higher performance than fixed regulators, the device includes on-chip current limiting, thermal overload protection, and safe-operating-area protection. All overload protection remains fully functional if the ADJUST terminal is disconnected.

Normally, no capacitors are needed unless the device is more than 6 inches from the input filter capacitors, in which case an input bypass capacitor is needed. An optional output capacitor can be added to improve transient response. The ADJUST terminal can be bypassed to achieve very high ripple-rejection ratios, which are difficult to achieve with standard 3-terminal regulators.

The LM317M is characterized for operation over the virtual junction temperature range of 0°C to 125°C.



The OUTPUT terminal is in electrical contact with the mounting base.



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

PRODUCTION DATA information is current as of publication date. Products conform to specifications per the terms of Texas Instruments standard warranty. Production processing does not necessarily include testing of all parameters.

 **TEXAS
INSTRUMENTS**

POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

Copyright © 2001, Texas Instruments Incorporated

LM317M

3-TERMINAL ADJUSTABLE REGULATOR

SLVS297C – APRIL 2000 – REVISED NOVEMBER 2001

absolute maximum ratings over operating temperature range (unless otherwise noted)[†]

Input-to-output differential voltage, $V_I - V_O$	40 V
Package thermal impedance, θ_{JA} (see Notes 1 and 2)	28°C/W
Lead temperature 1,6 mm (1/16 inch) from case for 10 seconds	28°C
Storage temperature range, T_{stg}	–65°C to 150°C

[†] Stresses beyond those listed under “absolute maximum ratings” may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under “recommended operating conditions” is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

NOTES: 1. Maximum power dissipation is a function of $T_J(\max)$, θ_{JA} , and T_A . The maximum allowable power dissipation at any allowable ambient temperature is $P_D = (T_J(\max) - T_A)/\theta_{JA}$. Operating at the absolute maximum T_J of 150°C can impact reliability.
2. The package thermal impedance is calculated in accordance with JESD 51-5.

recommended operating conditions

	MIN	MAX	UNIT
$V_I - V_O$ Input-to-output voltage differential		37	V
I_O Output current		0.5	A
T_J Operating virtual junction temperature	0	125	°C

electrical characteristics over recommended operating virtual-junction temperature range, $V_I - V_O = 5$ V, $I_O = 0.1$ A (unless otherwise noted)

PARAMETER	TEST CONDITIONS [‡]	MIN	TYP	MAX	UNIT
Line regulation (see Note 3)	$V_I - V_O = 3$ V to 40 V	$T_J = 25^\circ\text{C}$	0.01	0.04	%V
		Full temperature range	0.02	0.07	
Load regulation	$I_O = 10$ mA to 500 mA	$T_J = 25^\circ\text{C}$	0.1	0.5	%V _O
		Full temperature range	0.3	1.5	
ADJUST terminal current			50	100	μA
ADJUST terminal current change	$V_I - V_O = 3$ V to 40 V, $I_O = 10$ mA to 500 mA		0.2	5	μA
Reference voltage	$V_I - V_O = 3$ V to 40 V, $I_O = 10$ mA to 500 mA	1.2	1.25	1.3	V
Output-voltage temperature stability			0.7%		
Minimum load current to maintain regulation			3.5	10	mA
Maximum output current	$V_I - V_O \leq 15$ V	500	900		mA
	$V_I - V_O = 40$ V, $P_D \leq P_D(\max)$, $T_J = 25^\circ\text{C}$	150	250		
Output noise voltage (% of V _O)	$f = 10$ Hz to 10 KHz, $T_J = 25^\circ\text{C}$		0.003%		
Ripple rejection (see Note 4)	$V_O = 10$ V, $f = 120$ Hz, $T_J = 25^\circ\text{C}$	$C_{ADJ} = 0$	65		dB
		$C_{ADJ} = 10$ μF	66	80	
Long-term stability	$T_J = 125^\circ\text{C}$		0.3	1	%/1k Hrs

[‡] Pulse-testing techniques are used to maintain the junction temperature as close to the ambient temperature as possible.

NOTES: 3. Input voltage regulation is expressed here as the percentage change in output voltage per 1-V change at the input.

4. C_{ADJ} is connected between the ADJUST terminal and ground.



POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

TYPICAL CHARACTERISTICS




Figure 1




Figure 2




Figure 3




Figure 4

LM317M

3-TERMINAL ADJUSTABLE REGULATOR

SLVS297C – APRIL 2000 – REVISED NOVEMBER 2001

TYPICAL CHARACTERISTICS




Figure 5




Figure 6




Figure 7




Figure 8

TYPICAL CHARACTERISTICS




Figure 9




Figure 10




Figure 11

LM317M

3-TERMINAL ADJUSTABLE REGULATOR

SLVS297C – APRIL 2000 – REVISED NOVEMBER 2001

TYPICAL CHARACTERISTICS




Figure 12

TYPICAL CHARACTERISTICS

LOAD TRANSIENT RESPONSE





Figure 13

LM317M

3-TERMINAL ADJUSTABLE REGULATOR

SLVS297C – APRIL 2000 – REVISED NOVEMBER 2001

APPLICATION INFORMATION



NOTES: A. C_{in} is not required unless the LM317M is more than 6 inches from the input filter capacitors.

B. C_O improves transient response, but is not needed for stability.

V_{out} is calculated as shown:

$$V_{out} = V_{ref} \left(1 + \frac{R_2}{R_1} \right) + (I_{Adj} \times R_2)$$

Because I_{Adj} is typically 50 μA , it is negligible in most applications.

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Mailing Address:

Texas Instruments
Post Office Box 655303
Dallas, Texas 75265