



44 FARRAND STREET
BLOOMFIELD, NJ 07003
(973) 748-5089

NTE610 thru NTE614 Voltage Variable Capacitance Diode (Tuning Diode)

Description:

These diodes are designed for high volume requirements of FM Radio and TV tuning and AFC, general frequency control and tuning applications; providing solid-state reliability in replacement of mechanical tuning methods.

Features:

- High Q with Guaranteed Minimum Values
- Controlled and Uniform Tuning Ratio
- Standard Capacitance Tolerance – 10%

Absolute Maximum Ratings:

Reverse Voltage, V_R	30V
Forward Current, I_F	200mA
Device Dissipation ($T_A = 25^\circ\text{C}$), P_D	280mW
Derate Above 25°C	2.8mW/ $^\circ\text{C}$

Note 1. The NTE611 & NTE612 are **discontinued** devices and no longer available.

Electrical Characteristics: ($T_A = +25^\circ\text{C}$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Reverse Breakdown Voltage	$V_{(BR)R}$	$I_R = 10\mu\text{A}$	30	—	—	V
Reverse Voltage Leakage Current	I_R	$V_R = 25\text{V}$, $T_A = +25^\circ\text{C}$	—	—	0.1	μA
Series Inductance	L_S	$f = 250\text{MHz}$, Lead Length $\sim 1/16''$	—	6	—	nH
Case Capacitance	C_C	$f = 1\text{MHz}$, Lead Length $\sim 1/16''$	—	0.18	—	pF
Diode Capacitance Temperature Coefficient	TC_C	$V_R = 4\text{V}$, $f = 1\text{MHz}$	—	280	400	ppm/ $^\circ\text{C}$
Diode Capacitance NTE610	C_T	$V_R = 4\text{V}$, $f = 1\text{MHz}$	6.1	6.8	7.5	pF
NTE611			9.0	10.0	11.0	pF
NTE612			10.8	12.0	13.2	pF
NTE613			19.8	22.0	24.2	pF
NTE614			29.7	33.0	36.3	pF

Electrical Characteristics (Cont'd): ($T_A = +25^\circ\text{C}$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Figure of Merit NTE610	Q	$V_R = 4\text{V}$, $f = 50\text{MHz}$	450	—	—	
NTE611, NTE612			400	—	—	
NTE613			350	—	—	
NTE614			200	—	—	
Tuning Ratio NTE610	TR	C_2/C_{30} , $f = 1\text{MHz}$	2.5	2.7	3.2	
NTE611, NTE612, NTE613			2.5	2.9	3.2	
NTE614			2.5	3.0	3.2	

