

DUAL OPERATIONAL AMPLIFIER

■ GENERAL DESCRIPTION

The **NJM2740** is a dual low supply voltage operational amplifier with low saturation output voltage.
It can operate with single supply when proper input bias has given.
It is suitable for audio section of portable sets and PCs.

■ PACKAGE OUTLINE




NJM2740M

NJM2740V

■ FEATURES

- Operating Voltage (± 1.1 to ± 3.5 V)
- Low Saturation Output Voltage (± 2.2 V typ. at $R_L=2.5\text{k}\Omega$)
- High Slew Rate (4V/ μ s typ.)
- Bipolar Technology
- Package Outline DMP8,SSOP8


■ PIN CONFIGURATION



PIN FUNCTION

- | | |
|------------------|---------|
| 1. | OUTPUT1 |
| 2.- | INPUT1 |
| 3.+ | INPUT1 |
| 4.V | |
| 5.+ | INPUT2 |
| 6.- | INPUT2 |
| 7.OUTPUT2 | |
| 8.V ⁺ | |

■ EQUIVALENT CIRCUIT



NJM2740

■ ABSOLUTE MAXIMUM RATINGS

(Ta=25°C)

PARAMETER	SYMBOL	RATINGS	UNIT
Supply Voltage	V ⁺ /V ⁻	±4	V
Differential Input Voltage	V _{ID}	±7	V
Common Mode Input Voltage	V _{IC}	±3.5	V
Power Dissipation	P _D	300 (DMP8) 250 (SSOP8)	mW
Operating Temperature Range	Topr	-40 to +85	°C
Storage Temperature Range	Tstg	-40 to +125	°C

■ RECOMMENDED OPERATING CONDITION

(Ta=25°C)

PARAMETER	SYMBOL	TEST CONDITION	MIN	TYP	MAX	UNIT
Operating Voltage Range	V ⁺ /V ⁻		±1.1	-	±3.5	V

■ DC CHARACTERISTICS

(V⁺/V⁻=±2.5V, Ta=25°C)

PARAMETER	SYMBOL	TEST CONDITION	MIN	TYP	MAX	UNIT
Operating Current	I _{CC}	No Signal, R _L =infinite	-	3.5	5	mA
Input Offset Voltage	V _{IO}	R _S ≤10kΩ	-	1.0	6.0	mV
Input Bias Current	I _B		-	100	300	nA
Input Offset Current	I _{IO}		-	5	100	nA
Open Loop Voltage Gain	A _V	R _L >10kΩ	60	80	-	dB
Common Mode Rejection	CMR		60	74	-	dB
Supply Voltage Rejection	SVR	V ⁺ /V ⁻ =±1.2 to 3.5V	60	80	-	dB
Maximum Output Voltage	V _{OM}	R _L >2.5kΩ	±2	±2.2	-	V
Input Common Mode Voltage Range	V _{ICM}		-1.4/ +1.5	-	-	V

■ AC CHARACTERISTICS

(V⁺/V⁻=±2.5V, Ta=25°C)







PARAMETER	SYMBOL	TEST CONDITION	MIN	TYP	MAX	UNIT
Gain Bandwidth product	GB	f=10kHz	-	12	-	MHz

■ TRANSIENT CHARACTERISTICS






(V⁺/V⁻=±2.5V, Ta=25°C)






PARAMETER	SYMBOL	TEST CONDITION	MIN	TYP	MAX	UNIT
Slew Rate	SR	A _V =1, V _{IN} =±1V	-	4	-	V/μs

■ TYPICAL CHARACTERISTICS




NJM2740






NJM2740


Voltage Gain & Phase vs. Frequency
 $V+/V=-\pm 1.1V$, $GV=40dB$, $RF=100k\Omega$,
 $RG=1k\Omega$, $RL=2.5k\Omega$, $CL=0pF$




Voltage Gain & Phase vs. Frequency
 $V+/V=-\pm 2.5V$, $GV=40dB$, $RF=100k\Omega$,
 $RG=1k\Omega$, $RL=2.5k\Omega$, $CL=0pF$




Voltage Gain & Phase vs. Frequency
 $V+/V=-\pm 3.5V$, $GV=40dB$, $RF=100k\Omega$,
 $RG=1k\Omega$, $RL=2.5k\Omega$, $CL=0pF$



Voltage Gain & Phase vs. Frequency
 $GV=40dB$, $RF=100k\Omega$, $RG=1k\Omega$,
 $RL=2.5k\Omega$, $CL=0pF$, $Ta=25^\circ C$




Peak Gain of Voltage Follower
 $V+/V=2.5V$, $GV=0dB$, $RS=50\Omega$,
 $RL=10k\Omega$, $Ta=+25^\circ C$




Phase Margin vs. Load Capacitance


$V+/V=-\pm 2.5V$, $GV=40dB$,
 $RF=100k\Omega$, $RG=1k\Omega$, $RL=2.5k\Omega$, $Ta=+25^\circ C$




**Equivalent Input Noise Voltage
vs. Input Resistance**




**Total Harmonic Distortion
vs. Output Voltage**



Pulse Response (Rise)
V₊/V₋=±2.5V, AV=0dB, f=100kHz,
VIN=±1V, RL=10kΩ, CL=0pF



Pulse Response (Fall)
V₊/V₋=±2.5V, AV=0dB, f=100kHz,
VIN=±1V, RL=10kΩ, CL=0pF



■ MEMO

[CAUTION]

The specifications on this databook are only given for information , without any guarantee as regards either mistakes or omissions. The application circuits in this databook are described only to show representative usages of the product and not intended for the guarantee or permission of any right including the industrial rights.