

Contents

Features.....	1
Applications.....	1
Block Diagram	1
Selection Guide.....	2
Pin Assignment.....	2
Absolute Maximum Ratings	2
Electrical Characteristics	3
Measurement Circuits.....	7
Operation	8
Recommended Selection of Series Products and External Parts	12
Standard Circuits	15
Design Precautions.....	16
Application Circuits	17
Dimensions	19
Marking	19
Taping.....	20
Temperature Characteristics	21
Power Supply Dependency Characteristics.....	21
Transitory Response Characteristics.....	23
Reference Data.....	26
Frequently Asked Questions.....	31

STEP-UP SWITCHING REGULATOR FOR LCD BIAS SUPPLY

S-8330/8331 Series

The S-8330/8331 Series is a CMOS PWM-control step-up switching regulator which mainly consists of a reference voltage source, an oscillation circuit, a power MOS FET (for S-8330 Series), and an error amplifier. The output voltage can adjust by built-in Electric volume circuit, and equip with shutdown function. The S-8330 Series is low current consumption because of CMOS structure, and a step-up switching regulator constructed by externally connecting only a coil, a capacitor and a diode. This feature, along with its 8-Pin SSOP package and a few external components, makes the S-8330 Series ideal for LCD bias generators of portable equipment. For applications requiring a high output current, products used with an external transistor (S-8331 Series) are also available.

■ Features

- Maximum output voltage: 20 V to 30 V (2 V step)
12 V range can be adjusted by electric volume
- Output current: 5mA ($V_{IN}=5\text{ V}, V_{OUT}=30\text{ V}$)
- Low current consumption :
During operation: 100 μA (typ.) ($V_{IN}=5\text{ V}$ 180 kHz)
During shutdown : 1.0 μA (max.)
- Shutdown function: Stepping up operation is stopped ,
and Vout pin is shorted to GND while shutdown.
- Input voltage range: 2.0 to 9.0 V
- Soft start function: 3 msec (typ.)
- Built-in CR oscillation circuit:
Oscillating frequency: 180 kHz (typ.) (A series)
Oscillating frequency: 50 kHz (typ.) (B series)
- 8-pin SSOP plastic package
- 8-bit built-in electric volume circuit
- External transistor type is available (S-8331 Series)

■ Applications

- Power supplies for medium type or large type LCD panel.
- Power supplies for portable devices such as pagers, handy calculators, and remote controllers
- Constant voltage power supplies for cameras, video equipment, and communications equipment

■ Block Diagram





Figure 1 Block Diagram

■ Selection Guide

1. Product Name



2. Product list

Output voltage range (V)	S-8330AXXFS Series	S-8330BXXFS Series	S-8331AXXFS Series
8 to 20	S-8330A20FS-T2	S-8330B20FS-T2	S-8331A20FS-T2
10 to 22	S-8330A22FS-T2	S-8330B22FS-T2	S-8331A22FS-T2
12 to 24	S-8330A24FS-T2	S-8330B24FS-T2	S-8331A24FS-T2
14 to 26	S-8330A26FS-T2	S-8330B26FS-T2	S-8331A26FS-T2
16 to 28	S-8330A28FS-T2	S-8330B28FS-T2	S-8331A28FS-T2
18 to 30	S-8330A30FS-T2	S-8330B30FS-T2	S-8331A30FS-T2

■ Pin Assignment




Figure 2 Pin Assignment

Pin No.	Pin name	Functions
1	VDIN	Electric volume data input pin
2	VCLK	Electric volume clock input pin
3	VSTRB	Electric volume strobe signal input pin
4	V _{OUT}	Output voltage pin
5	V _{IN}	Power supply pin
6	CONT	External inductor connection pin (Note 1)
	EXT	External transistor connection pin (Note 2)
7	ON/OFF	Shutdown pin
		"H":normal operation (stepping up operation)
		"L":stop stepping up operation
8	V _{SS}	GND pin

Note 1: S-8330 Series: Open drain output

Note 2: S-8331 Series: CMOS output

■ Absolute Maximum Ratings

Note: Built-in protect circuit for static electricity on chip.

However, prevent a charge of static electricity which exceeds the capacity of the protection circuit.

(Unless otherwise specified: Ta=25°C)

Parameter	Symbol	Ratings	Unit
V _{OUT} pin voltage	VOUT	V _{SS} -0.3 to 33	V
CONT pin voltage	VCONT	V _{SS} -0.3 to 33	V
CONT pin current	ICONT	300	mA
EXT pin voltage	VEXT	V _{SS} -0.3 to VOUT+0.3	V
EXT pin current	IEXT	±50	mA
Input voltage	VIN,VCLK,VDIN, VSTRB,ON/OFF	V _{SS} -0.3 to 10	V
Power dissipation	PD	300	mW
Operating temperature range	TOPR	-20 to +70	°C
Storage temperature range	TSTG	-40 to +125	°C

■ Electrical Characteristics

1. S-8330A Series

Step-Up Switching Regulator

(Unless otherwise specified: Ta=25°C)

Items	Symbols	Conditions		Min.	Typ.	Max.	Unit	Mea.Circ.
Output voltage range	VOUT	S-8330A20FS		8	—	20	V	5
		S-8330A22FS		10	—	22		
		S-8330A24FS		12	—	24		
		S-8330A26FS		14	—	26		
		S-8330A28FS		16	—	28		
		S-8330A30FS		18	—	30		
Input voltage	VIN			2.0	—	9.0	V	2
Current consumption 1	ISS1	VIN =5V, VOUT = Output voltage Max.		—	100	200	μA	4
Current consumption 2	ISS2	VIN =2V, VOUT = Output voltage Min.		—	50	100	μA	4
Current consumption during power off	ISSS	Power off pin =VDATA=0V,VIN=VCLK=VSTRB=5V		—	—	1.0	μA	4
Switching current	ISW	VCONT=0.4V		100	200	—	mA	—
Switching transistor leakage current	ISWQ	Power off pin =0V , VCONT=9V		—	—	1.0	μA	3
Line regulation	ΔVOUT1	VIN =3V to 6V	S-8330A20FS	—	±300	—	mV	5
			S-8330A22FS	—	±330	—		
			S-8330A24FS	—	±360	—		
			S-8330A26FS	—	±390	—		
			S-8330A28FS	—	±420	—		
			S-8330A30FS	—	±450	—		
Load regulation	ΔVOUT2	VIN =5V IOUT=output voltage/2.4MΩ to output voltage/24kΩ		—	±30	—	mV	5
Output voltage temperature coefficient	ΔVOUT /ΔTa	Ta= -20°C to +70°C	S-8330A20FS	—	±1.0	—	mV /°C	5
			S-8330A22FS	—	±1.1	—		
			S-8330A24FS	—	±1.2	—		
			S-8330A26FS	—	±1.3	—		
			S-8330A28FS	—	±1.4	—		
			S-8330A30FS	—	±1.5	—		
Oscillating frequency	fosc	VOUT =output voltage×0.95 Measure waveform at CONT pin		144	180	216	kHz	2
Maximum duty ratio	Max Duty	VOUT =output voltage×0.95 Measure waveform at CONT pin		60	72	84	%	2
Power off terminal input voltage	VSH1	VOUT =output voltage×0.95	VIN ≥ 3.0V	2.4	—	—	V	2
	VSH2	Check oscillation at CONT pin	VIN <3.0V	1.6	—	—		
	VSL	VOUT =output voltage×0.95 Check oscillation stop at CONT pin	—	—	0.4			
Power off terminal input leakage current	ISL	VIN =9V		-1	—	1	μA	1
Soft start time	TSS			1	3	6	ms	—
Efficiency	EFFI			—	85	—	%	5

Externally attached parts:

Coils : CD54 (47μH) of Sumida Electric Co., Ltd.

Diodes : MA720 Schottky type of Matsushita Electronic Components Co., Ltd.

Capacitors: F93 tantalum type (two circuits of 50V, 4.7μF are connected in parallel) of Nichicon Corporation

VIN=5V, VOUT=VOUT Max. IOUT= output voltage /24kΩ

ON/OFF=5V, VDATA=VCLK=VSTRB=0V

Note: Output voltage specified above is the typical value of the output voltage.

2. S-8330B Series

Step-Up Switching Regulator

(Unless otherwise specified: Ta=25°C)

Item	Symbol	Conditions	Min.	Typ.	Max.	Unit	Mea. Cir.
Output voltage range	VOUT	S-8330B20FS	8	—	20	V	5
		S-8330B22FS	10	—	22		
		S-8330B24FS	12	—	24		
		S-8330B26FS	14	—	26		
		S-8330B28FS	16	—	28		
		S-8330B30FS	18	—	30		
Input voltage	VIN		2.0	—	9.0	V	2
Current consumption 1	ISS1	VIN=5V, VOUT=Output voltage Max.	—	40	80	μA	4
Current consumption 2	ISS2	VIN=2V, VOUT=Output voltage Min.	—	20	40	μA	4
Current consumption during power off	ISSS	Power off pin =VDATA=0V, VIN=VCLK=VSTRB=5V	—	—	1.0	μA	4
Switching current	ISW	VCONT=0.4V	100	200	—	mA	—
Switching transistor leakage current	ISWQ	Power off pin=0V, VCONT=9V	—	—	1.0	μA	3
Line regulation	ΔVOUT1	VIN=3V to 6V	S-8330B20FS	—	±300	mV	5
			S-8330B22FS	—	±330		
			S-8330B24FS	—	±360		
			S-8330B26FS	—	±390		
			S-8330B28FS	—	±420		
			S-8330B30FS	—	±450		
Load regulation	ΔVOUT2	VIN=5V IOUT=Output voltage/2.4MΩ to Output voltage/24kΩ	—	±30	—	mV	5
Output voltage Temperature coefficient	ΔVOUT /ΔTa	Ta=−20°C to +70°C	S-8330B20FS	—	±1.0	mV /°C	5
			S-8330B22FS	—	±1.1		
			S-8330B24FS	—	±1.2		
			S-8330B26FS	—	±1.3		
			S-8330B28FS	—	±1.4		
			S-8330B30FS	—	±1.5		
Oscillating frequency	fosc	VOUT=Output voltage×0.95 Measure waveform at CONT pin	40	50	60	kHz	2
Maximum duty ratio	Max Duty	VOUT=Output voltage×0.95 Measure waveform at CONT pin	60	72	84	%	2
Power off pin Input voltage	VSH1	VOUT=Output voltage×0.95 VIN ≥3.0V	2.4	—	—	V	2
	VSH2	Check oscillation at CONT pin VIN <3.0V	1.6	—	—		
	VSL	VOUT=Output voltage×0.95 Check oscillation stop at CONT pin	—	—	0.4		
Power off pin Input leakage current	ISL	VIN=9V	-1	—	1	μA	1
Soft start time	TSS		3	10	20	ms	—
Efficiency	EFFI		—	85	—	%	5

Externally attached parts:

Coils : CD54 (47μH) of Sumida Electric Co., Ltd.

Diodes : MA720 Schottky type of Matsushita Electronic Components Co., Ltd.

Capacitors: F93 tantalum type (two circuits of 50V, 4.7μF are connected in parallel) of Nichicon Corporation

VIN=5V, VOUT=VOUT Max. IOUT= output voltage /24kΩ

ON/OFF=5V, VDATA=VCLK=VSTRB=0V

Note: Output voltage specified above is the typical value of the output voltage.

3. S-8331A Series

Step-Up Switching Regulator

(Unless otherwise specified: Ta=25°C)

Step-Up Switching Regulator				(Unless otherwise specified, T _a =25°C)				
Item	Symbol	Conditions		Min.	Typ.	Max.	Unit	Mea. Cir.
Output voltage range	V _{OUT}	S-8330A20FS		8	—	20	V	6
		S-8330A22FS		10	—	22		
		S-8330A24FS		12	—	24		
		S-8330A26FS		14	—	26		
		S-8330A28FS		16	—	28		
		S-8330A30FS		18	—	30		
Input voltage	V _{IN}			2.0	—	9.0	V	2
Current consumption 1	ISS1	V _{IN} =5V, V _{OUT} =Output voltage Max.		—	50	100	μA	4
Current consumption 2	ISS2	V _{IN} =2V, V _{OUT} =Output voltage Min.		—	25	50	μA	4
Current consumption during power off	ISS3	Power off pin =VDATA=0V, V _{IN} =VCLK=VSTRB=5V		—	—	1.0	μA	4
Output current at EXTpin	IEXTH	VEXT=V _{IN} -0.4V		3.0	5.0	—	mA	—
	IEXTL	VEXT=0.4V		5.0	8.0	—	mA	—
Line regulation	ΔV _{OUT1}	V _{IN} =3V to 6V	S-8331A20FS	—	±300	—	mV	6
			S-8331A22FS	—	±330	—		
			S-8331A24FS	—	±360	—		
			S-8331A26FS	—	±390	—		
			S-8331A28FS	—	±420	—		
			S-8331A30FS	—	±450	—		
Load regulation	ΔV _{OUT2}	V _{IN} =5V I _{OUT} =Output voltage/2.4MΩ to Output voltage/24kΩ		—	±30	—	mV	6
Output voltage Temperature coefficient	ΔV _{OUT} /ΔT _a	T _a =-20°C to +70°C	S-8331A20FS	—	±1.0	—	mV /°C	6
			S-8331A22FS	—	±1.1	—		
			S-8331A24FS	—	±1.2	—		
			S-8331A26FS	—	±1.3	—		
			S-8331A28FS	—	±1.4	—		
			S-8331A30FS	—	±1.5	—		
Oscillating frequency	fosc	V _{OUT} =Output voltage×0.95 Measure waveform at EXT pin		144	180	216	kHz	2
Maximum duty ratio	Max Duty	V _{OUT} =Output voltage×0.95 Measure waveform at EXT pin		60	72	84	%	2
Power off pin Input voltage	VSH1	V _{OUT} =Output voltage×0.95	V _{IN} ≥3.0V	2.4	—	—	V	2
	VSH2	Check oscillation at EXT pin	V _{IN} <3.0V	1.6	—	—		
	VSL	V _{OUT} =Output voltage×0.95 Check oscillation stop at EXT pin	—	—	0.4			
Power off pin Input leakage current	ISL	V _{IN} =9V		-1	—	1	μA	1
Soft start time	TSS			1	3	6	ms	—
Efficiency	EFFI			—	85	—	%	6

Externally attached parts:

Coils : CD54 (47μH) of Sumida Electric Co., Ltd.

Diodes : MA720 Schottky type of Matsushita Electronic Components Co., Ltd.

Capacitors: F93 tantalum type (two circuits of 50V, 4.7μF are connected in parallel) of Nichicon Corporation.

Transistors: 2SD1624 of Sanyo Electric Inc.

Base resistance (Rb):1.0kΩ

Base capacitor (Cb):2200pF (ceramic type)

VIN=5V, VOUT=VOUT Max. IOUT= output voltage/24kΩ

ON/OFF=5V, VDATA=VCLK=VSTRB=0V


Note: Output voltage specified above is the typical value of the output voltage.

4. Characteristics Common to S-8330/31Series

Electric Volume

(Unless otherwise specified: Ta=25°C)


Item	Symbol	Conditions	Min.	Typ.	Max.	Unit	Mea. cir.
Output voltage range (Note 1)	VOUT	S-833XX20FS	8	—	14	V	5 (6)
			14	—	20		
		S-833XX22FS	10	—	16		
			16	—	22		
		S-833XX24FS	12	—	18		
			18	—	24		
		S-833XX26FS	14	—	20		
			20	—	26		
		S-833XX28FS	16	—	22		
			22	—	28		
		S-833XX30FS	18	—	24		
			24	—	30		
Potential division accuracy			—	—	±2.4	%	5 (6)
Electric volume resolution			—	1/256	—		5 (6)
Error in linearity (Note 1)			—	—	±1/2	LSB	5 (6)
Data setup time	tsc		0.5	—	—	μs	—
Data hold time	thc		0.5	—	—	μs	—
VCLK falling edge to VSTRB rising edge	tss		0.5	—	—	μs	—
VSTRB pulse width	tda		0.5	—	—	μs	—
VSTRB falling edge to VCLK rising edge	ths		0.5	—	—	μs	—
VCLK pulse width	tdc		0.5	4.17	—	μs	—
VCLK period	ttc		5	8.33	—	μs	—
VDIN,VCLK,VSTRB Input voltage .H. level	VSHC1	V _{IN} ≥3.0V	2.4	—	—	V	—
	VSHC2	V _{IN} <3.0V	1.6	—	—		
VDIN,VCLK,VSTRB Input voltage .L. level	VSLC		—	—	0.2		
VDIN,VCLK,VSTRB Input leakage current	ISLC	V _{IN} =9V	-1	—	1	μA	1

**Figure 3 Data Input Timing**


Note 1: An electric volume has 8-bit resolution. However, its error in linearity may exceed ±1/2LSB only before and after switching from 127 to 128 (from 01111111 to 10000000) and vice versa. When the electric volume is used within the variable range of 12 V, its error in linearity corresponds to 6 bits (±2.4% potential division accuracy is ensured).

■ Measurement Circuits

1




2




Not needed in the *S-8331 Series.

3




4



Not needed in the *S-8331 Series.

5



6




Figure 4 Measurement Circuits

■ Operation

1. Set-Up DC-DC Converter

The S-8330/31 Series is a DC-DC converter using a pulse width modulation method (PWM) with low current consumption. Conventional PFM DC/DC converters have a drawback. Namely, an increase in the ripple voltage occurs because pulses are skipped when low output load current flows and the ripple frequency of the output voltage varies. In the S-8330/31 Series, the pulse width varies in the range of 0 % to 72 % depending upon the load current, but the switching frequency does not vary. This allows the ripple voltage due to switching to be reduced with a filter. Also, the internal soft start circuit incorporated into the S-8330/31 Series controls overshoot of the output voltage when the power is turned on or when the ON/OFF pin is "H" level.




Figure 5 Step-Up DC-DC Converter

The following are fundamental equations of set-up switching regulators [(1) to (7)] (see Figure 5).

The pin voltage at CONT immediately after M1 is turned ON (current I_L which flows into L is zero):

$$V_A = V_S \quad \dots\dots\dots (1)$$

(V_S : Not saturated voltage of M1)

Change in I_L with time:

$$\frac{dI_L}{dt} = \frac{V_L}{L} = \frac{V_{IN} - V_S}{L} \quad \dots\dots\dots (2)$$

Integration of the above equation (I_L) is as follows:

$$I_L = \left(\frac{V_{IN} - V_S}{L} \right) \cdot t \quad \dots\dots\dots (3)$$

I_L flows into L during t_{ON} . The time is determined depending upon the oscillating frequency of the OSC.

The peak current (I_{PK}) after t_{ON} :

$$I_{PK} = \left(\frac{V_{IN} - V_S}{L} \right) \cdot t_{ON} \quad \dots\dots\dots (4)$$

The energy stored in L is represented by $1/2 \cdot L (I_{PK})^2$.

When M1 is turned OFF (t_{OFF}), the energy stored in L is transmitted through a diode. Then reverse voltage (V_L) generates.

V_L :

$$V_L = (V_{OUT} + V_D) - V_{IN} \quad \dots\dots\dots (5)$$

(V_D : Diode forward voltage)

The pin voltage at CONT rises only by the voltage corresponding to $V_{OUT} + V_D$.

A change in the current (I_L) which flows through a diode into V_{OUT} during t_{OFF} :

$$\frac{dI_L}{dt} = \frac{V_L}{L} = \frac{V_{OUT} + V_D - V_{IN}}{L} \quad \dots\dots\dots (6)$$

Integration of the above equation is as follows :

$$I_L = I_{PK} - \left(\frac{V_{OUT} + V_D - V_{IN}}{L} \right) \cdot t \quad \dots\dots\dots (7)$$

During t_{ON} , the energy is stored in L and is not transmitted to V_{OUT} . When output current (I_{OUT}) flows from V_{OUT} , the energy of the capacitor (C_{OUT}) is consumed. As a result, the pin voltage at C_{OUT} decreases and goes to the lowest value after t_{ON} . When M1 is turned OFF, the energy stored in L is transmitted through a diode into C_{OUT} , and the pin voltage at C_{OUT} rises drastically. V_{OUT} is a time function that indicates the maximum value (ripple voltage V_{P-P}) when the current flowing into V_{OUT} through diode and load current I_{OUT} match. Next, the ripple voltage is found out based on the following equations:

I_{OUT} when the time is set to t_1 until V_{OUT} reaches the maximum level immediately after t_{ON} :

$$I_{OUT} = I_{PK} - \left(\frac{V_{OUT} + V_D - V_{IN}}{L} \right) \cdot t_1 \quad \dots\dots\dots (8)$$

$$\therefore t_1 = (I_{PK} - I_{OUT}) \cdot \left(\frac{L}{V_{OUT} + V_D - V_{IN}} \right) \quad \dots\dots\dots (9)$$

t_{OFF} when $I_L = 0$ (the energy of the inductor is completely transmitted). Based on equation (7)

$$\left(\frac{L}{V_{OUT} + V_D - V_{IN}} \right) = \frac{t_{OFF}}{I_{PK}} \quad \dots\dots\dots (10)$$

When substituting equation (10) for equation (9):

$$t_1 = t_{OFF} - \left(\frac{I_{OUT}}{I_{PK}} \right) \cdot t_{OFF} \quad \dots\dots\dots (11)$$

Electric charge (ΔQ_1) which is charged in C_{OUT} during t_1 :

$$\begin{aligned} \Delta Q_1 &= \int_0^{t_1} I_L dt = I_{PK} \cdot \int_0^{t_1} dt - \frac{V_{OUT} + V_D - V_{IN}}{L} \cdot \int_0^{t_1} t dt \\ &= I_{PK} \cdot t_1 - \frac{V_{OUT} + V_D - V_{IN}}{L} \cdot \frac{1}{2} t_1^2 \quad \dots\dots\dots (12) \end{aligned}$$

When substituting equation (12) for equation (9):

$$\Delta Q_1 = I_{PK} - \frac{1}{2} (I_{PK} - I_{OUT}) \cdot t_1 = \frac{I_{PK} + I_{OUT}}{2} \cdot t_1 \quad \dots\dots\dots (13)$$

A rise in voltage (V_{P-P}) due to ΔQ_1 :

$$V_{P-P} = \frac{\Delta Q_1}{C_{OUT}} = \frac{1}{C_{OUT}} \cdot \left(\frac{I_{PK} + I_{OUT}}{2} \right) \cdot t_1 \quad \dots\dots\dots (14)$$

When taking into consideration ESR (Electric Series Resistance) R_{ESR} of I_{OUT} and C_{OUT} during t_1 :

$$V_{P-P} = \frac{\Delta Q_1}{C_{OUT}} = \frac{1}{C_{OUT}} \cdot \left(\frac{I_{PK} + I_{OUT}}{2} \right) \cdot t_1 + \left(\frac{I_{PK} + I_{OUT}}{2} \right) \cdot R_{ESR} - \frac{I_{OUT} \cdot t_1}{C_{OUT}} \dots\dots\dots (15)$$

When substituting equation (15) for equation (11):

$$V_{P-P} = \frac{(I_{PK} - I_{OUT})^2}{2I_{PK}} \cdot \frac{t_{OFF}}{C_{OUT}} + \left(\frac{I_{PK} + I_{OUT}}{2} \right) \cdot R_{ESR} \dots\dots\dots (16)$$

The effective methods to reduce the ripple voltage are to maximize the capacitance of the capacitor connected to the output pin and to minimize ESR.

2. Power off pin (ON/OFF pin)

This pin stops and starts set up operation.

Turnig the power off pin to “L” stops the operation of the internal circuits excluding the electric volume, minimizes current consumption and short-circuits V_{OUT} pin to V_{SS} . At this time, current flows via coils and a diode at the input side into V_{SS} . Therefore, a switch to cut off the current is needed.

Figure 6 shows a circuit example using the NEC 2SJ356 (Pch MOS FET) as a current cutting switch. This circuit example turns ON and OFF the 2SJ356 in connection with the reset signal to the power off pin using a small signal transistor M_N (Nch MOS FET). A Zenor diode (ZD) is used for the purpose of clamping voltage so as not to apply high voltage (20V or more) of the rated voltage between the gate and the source of the 2SJ356. However, when the circuit is used at 20 V or below, a Zenor diode is not needed. Invalid current flowing into resistors R_A , R_B during step-up operation may affect the efficiency. Set R_A , R_B to the maximum level. If you set the resistance of R_A to the high value, a drop in the voltage occurs in resistor R_A due to off current of M_N and the current cutting switch 2SJ356 does not normally function. Be careful (Note that the efficiency characteristics shown in the reference data were measured without attaching a current cutting switch and is different from that shown in this example).




Figure 6 Circuit Example Using 2SJ356

The power off pin is configured as shown in Figure 7. DO NOT use this circuit under the floating state because the power off pin is not internally pulled up nor pulled down. If 0.4V to 2.4V when $V_{IN} \geq 3.0V$, 0.4V to 1.6V when $V_{IN} < 3.0V$ are applied, current consumption increases. DO NOT apply voltage. When the power off pin is not used, connect it to V_{IN} pin. The power off pin is not provided with hysteresis.

Power off pin	CR OSC	Output voltage
"H"	Operation	Setting value
"L"	Stop	V_{SS}




Figure 7

3. Electric Volume

The S-8330/31 series incorporates an electric volume with an 8-bit shift register and an 8-bit latch. The output voltage is variable in the width of 12 V. The output voltage can be held in the data transmission mode because the data read in the shift register is fetched into the latch by unsynchronized strobe input. Figure 8 shows a block diagram and timing charts.




Figure 8 Block Diagram and Timing

VDIN: Inputs data to the electric volume.

"Data 1" is input at "H" level; "Data 0" is input at "Low" level.

VCLK: Inputs clock to the electric volume.

Fetches data at VDIN pin into the shift register at the rising edge of clocks. When clocks of over 8 bits are input, the read data is shifted in succession for each clock, and data corresponding to 8 bits which was input lastly is valid.

VSTRB: Inputs strobe signal.

The contents of the shift register are latched by turning the strobe signal to "H." When the data fetched into the latch is directly transmitted to the electric volume, the output voltage changes. Data in the latch is held by turning the strobe signal to "L."




Figure 9 Linearity Accuracy

The electric volume has 8-bit resolution. An error in linearity may exceed $\pm 1/2\text{LSB}$ ($\pm 23.5\text{ mV}$) only before or after data changeover of $127 \leftrightarrow 128$ ($01111111 \leftrightarrow 10000000$) (see Figure 9).

The error in linearity corresponds to 6 bits ($\pm 93.8\text{ mV}$) when used in the 12 V variable range.

In an application where the variable range of output voltage is 6 V or less, it is possible to use it with high linearity accuracy with appropriate product selection. For example, if you want to change output voltage within the range from 12 V to 18 V, select the S-8330A24FS and use it within the range of $0 \leftrightarrow 127$ ($00000000 \leftrightarrow 01111111$). If so, high linearity accuracy (within $\pm 1/2\text{LSB}$) can be obtained.

The contents of the register must be reset because they are uncertain when powering on. If the power off pin is "L" level and step-up operation stops, the contents of the register are held inside the electric volume by applying voltage of 2 V or more between V_{IN} to V_{SS} . Data write and reset operation in the register are also available under this state. The register is reset by setting VCLK to "H" and VSTRB to "H." The output voltage is set to the minimum value. Power on under the state where the power off pin is being set to "L." Next, set VCLK to "H" and VSTRB to "H" to reset the contents of the register. Then, start step-up operation under the state where the power off pin is being set to "H."

[Note] If you start step-up operation without resetting the contents of the register after powering on, the maximum voltage is output to V_{OUT} , and the connected device or instrument may be broken or damaged. It is recommended to connect a pull down resistor to the power off pin if a problem may occur due to the maximum output voltage.

■ Recommended Selection of Series Products and External Parts

1. How to Select the Series Products

The S-8330/31 Series comes in three types depending upon the switching transistor attachment method (internal or external) and the oscillating frequency. As shown in Figure 10, respective output current targets differ to ensure high efficiency within the respective output current range. Select an appropriate series which meets your output current requirements (see the reference data for the output current and efficiency characteristics).

- ① S-8331A Series: The switching transistor is externally attached and the oscillating frequency is 180 kHz (typ.). Its target is the output current of 10 mA or more. High output voltage of 30 V or more is available by only attaching a simple external circuit to the S-8331A Series (see the S-8330 Series application circuit shown in Figure 17).
- ② S-8330A Series: The switching transistor is built in and the oscillating frequency is 180 kHz (typ.). Its target is the output current ranging from 1 mA to 10 mA. The oscillating frequency of the S-8330A Series is higher than that of the S-8330B Series. This minimizes ripple and ensures excellent transitory response characteristics.
- ③ S-8330B Series: The switching transistor is built in and the oscillating frequency is 50 kHz (typ.). Its target is output current of 1 mA or less. The self current consumption of the S-8330B Series is less than that of the S-8330A Series. This ensures high efficiency in the output current of about 0.1 mA or less.




Figure 10 S-8330/8331 Series Depending Upon Output Current

2. Inductor

The inductance value greatly affects I_{OUT} and efficiency η .

Figure 11 shows the dependency of I_{OUT} , η of the S-8330A and the S-8330B on "L."




Figure 11 Dependency of Inductance On Maximum Output Current and Efficiency

The smaller value L , the larger peak current I_{PK} . I_{OUT} reaches the maximum value in a certain value L . When decreasing value L further, the switching transistor falls short of the current drive ability and I_{OUT} decreases; when increasing value L , a loss due to I_{PK} of the switching transistor decreases and the efficiency reaches the maximum in a certain value L ; when increasing value L , a loss due to a series resistor of the coils increases. This worsens the efficiency. So, it is recommended to set value L to 22 to 100 μH in the S-8330A and 47 to 220 μH in the S-8330B, respectively.

Determine value L referring to the reference data because the maximum output current actually differs depending upon the input voltage.

Pay attention to the allowable current of the inductor when selecting an appropriate inductor. If current exceeding this allowable current flows into the inductor, magnetic saturation occurs in the inductor. This may lead to a serious drop in the efficiency and damage of the IC due to excessive current.

Select an appropriate inductor so that I_{PK} does not exceed this allowable current. Current I_{PK} in the non-continuous mode is represented by the following equation.

$$I_{PK} = \sqrt{\frac{2 I_{OUT} (V_{OUT} + V_D - V_{IN})}{f_{OSC} \cdot L}} \quad (A) \quad (17)$$

, where f_{OSC} is the oscillating frequency. Set V_D to approximately 0.4 V. For example, when you want a power source of input voltage $V_{IN}=5$ V, output voltage $V_{OUT}=30$ V, and load current $I_{OUT}=5$ mA, the S-8330A30FS responds to your requirements because $f_{OSC}=180$ kHz. When you set value L to 47 μH , $I_{PK}=174$ mA is found out as shown in equation (17). As a result, you can select an inductor for which value L is 47 μH and the allowable current is 174 mA or more. A limitation relating to the maximum value I_{PK} lies in the IC itself. Always use current I_{PK} at 500 mA or less.

3. Diode

Always use a diode which meets the following conditions.

- Low forward voltage: $V_F < 0.3V$
- Low switching speed: 500 ns max.
- Reverse direction voltage: $V_{OUT} + V_F$ or more
- Rating current: I_{PK} or more.

4. Capacitor (C_{IN} , C_{OUT})

Capacitor (C_{IN}) at the input side improves the efficiency by reducing the power impedance and stabilizing the input current. Select a value (C_{IN}) depending upon the impedance of the power supply used.

The standard capacitance is approximately 10 μ F. Select a capacitor (C_{OUT}) at the output side with small ESR (Electric Series Resistance) and large capacitance to stabilize the ripple voltage. The standard capacitance is approximately 10 μ F. It is particularly recommended to use a tantalum electrolytic capacitor with excellent low temperature and leakage current characteristics.

5. Externally-attached transistors (S-8331 Series)

The output current can be increased by externally attaching a transistor to the S-8331 Series. A bipolar (NPN) type or an enhancement (Nch) MOS FET type of transistor can be used as an external transistor.

5.1 Bipolar NPN type

Figure 15 shows a circuit example using the 2SD1624 manufactured by SANYO as a bipolar transistor (NPN). The drive ability to increase output current is determined by values h_{FE} and R_b of the bipolar transistor. A peripheral circuit example of the transistor is shown in Figure 12.




Figure 12 External Transistor Peripheral Circuit

It is recommended to select value R_b of approximately 1k Ω . Find necessary base current I_b from the bipolar transistor h_{FE} using $I_b = I_{PK}/h_{FE}$,

$$R_b = \frac{V_{IN} - 0.7}{I_b} \approx \frac{0.4}{|I_{EXT}|}$$

and select small value R_b . Small value R_b can increase the output current, but may worsen the efficiency. Also current may flow on the pulse or the voltage may drop due to wiring resistor. So, find the optimum value with experiments.

Attaching a speed-up capacitor C_b to the resistor R_b reduces switching loss and increases the efficiency.

$$\text{Value } C_b: \quad C_b \leq \frac{1}{2\pi \times R_b \times f_{OSC} \times 0.7}$$

5.2 Enhancement MOS FET type

Figure 13 shows a circuit example using the 2SK2159 manufactured by NEC as a MOS FET transistor (Nch). Use an Nch power MOS FET as a MOS FET. The EXT pin in the S-8331 series can drive a MOS FET with approx.1000 pF gate capacitance. The ON resistor of the MOS FET depends upon a difference between voltage input voltage V_{IN} and the threshold voltage of the MOS FET and thereby affects the output amperage and the efficiency. The gate voltage and the current of the MOS FET are supplied by input voltage V_{IN} . So pay attention if the input voltage is low. Also note that the IC will not function if the threshold voltage of the MOS FET is higher than the input voltage.




Figure 13 Circuit Example Using the 2SK2159

Standard Circuits

(1) S-8330 Series




Figure 14 S-8330 Series

(2) S-8331 Series




Figure 15 S-8331 Series

■ Design Precautions

- Mount capacitors, diodes, coils and other components as near as possible to the IC.
- Inherent ripple voltage or spike noise may generate in the switching regulator. Because it greatly depends upon the coils and the capacitors you use, check it using an actually-mounted model.
- Make sure that a loss in the switching transistor (particularly at high temperatures) does not exceed the allowable power dissipation.




Figure 16 8-Pin SSOP Power Dissipation (before mounting)

- Configure parts and components so that the line to the VSS pin (indicated by the bold line shown in Figure 17) becomes short as much as possible. If a resistor and/or an inductance component stays on the line, the VSS potential of the IC varies depending upon the switching current.




Figure 17 S-8330 Series Application Circuit

- When switching the output voltage by the electric volume, the soft start does not function. Pay attention to overshoot occurring when increasing the output voltage with a large width (refer to 5. Output Voltage Changeover shown in the transitory response characteristics).
- **Seiko Instruments Inc. shall not be responsible for any patent infringement by products including the S-8330/8331 Series in connection with the method of using the S-8330/8331 Series in such products, the product specifications or the country of destination thereof.**

■ Application Circuits

1. Large Size LCD Panel Drive Power Supply

This is a circuit example to drive a large size LCD panel (40 V/20 mA) at a 5-V power (5V±10%).




Figure 18 Large Size LCD Panel Drive Power Supply

This is an output voltage step-up circuit using the S-8331 Series. 30 V or more output voltage, i.e., the maximum voltage of the S-8330/8331 Series, is available by dividing the output voltage by external resistors RA and RB and feeding back to V_{OUT} pin. In the S-8331 Series the internal impedance of V_{OUT} pin varies by switching the electric volume. Therefore, a small signal NPN transistor (Tr. 3) is needed between the external voltage dividing resistor and V_{OUT} pin to convert the impedance.

The output voltage is represented by equation (18).

$$\text{Output voltage} = \left(\frac{RA + RB}{RB} \right) (V_{OUT} + V_{BE}) \quad (18)$$

(V_{OUT} : S-8331 V_{OUT} setting voltage
V_{BE} : Voltage between the base and the emitter of Tr. 3)

Pay attention to the following precautions when using this IC.

- Make sure that the switching transistor (Tr.1) and a Schottky diode (SD) have sufficient resistance against high output voltage you use. For example, the 2SD1624 manufactured by Sanyo and the MA789 manufactured by Matsushita are used in this circuit example for a switching transistor and a Schottky diode, respectively.
- When stopping step-up operation from the step-up operation state using the power off pin, V_{OUT} pin is shortcircuited to V_{SS} by an Nch transistor. Because of this, the output voltage is temporarily added to the area between the collector and the emitter of the transistor (Tr. 3). Always use a small signal transistor which is sufficient enough to withstand high output voltage (Tr. 3).
- The output voltage fails to stabilize when the output current falls short to 1 mA or less. In this case, add a capacitor CF between the output line and the V_{OUT} pin. The recommended capacitance of the capacitor is approx. 0.01μF. Select the best capacitance after checking it under actual operation conditions.

2. Medium Size LCD Panel Drive Power Supply for PDA

Voltage suitable for smart addressing (SA) and multiple line addressing (A) drive generates from a 3V- or 5 V-power supply. The following is a circuit example and its characteristics, targeted at positive voltage of approx. +15V/500μA and negative voltage of approx. -9V/500μA.






Figure 19 Medium Size LCD Panel Drive Power Supply for PDA


Output Current - Output voltage characteristics (Output Current Increase)



Output Current - Output Voltage Characteristics (Output Current Increase)



Output Current - Efficiency Characteristics (Output Current Increase)



This circuit stabilizes the positive output voltage +VOUT in the S-8330B Series. The negative output voltage -VOUT is determined and stabilized by the wiring ratio at the second and third sides in the transducer manufactured by Sumida (CEE93 6375-002 non-gap type) when the output current at the positive side is the same as that at the negative side. Also this circuit is targeted at applications at low load. The use of a 50 kHz product with low switching frequency improves the efficiency at load of approx. 500μA.

Pay attention to the following precautions when using it.

- Generally, the allowable current level of the thin transducer (CEE93 equivalent) is lower than that of the thin coil (CD54 equivalent). Make sure that the current flowing into the transducer under the specified operational conditions does not exceed the allowable current. For example, if load current is larger than 5 mA in the above circuit, magnetic saturation occurs and the IC may be damaged at the worst.
- When using an external gap-type transducer, the stability in the negative output voltage may worsen.

• **For external parts, contact**

Sumida Electric Co., Ltd.

Technical Sales & Support Center

2-4-8, Kanamachi, Katsushika-ku, Tokyo

TEL:03-3607-5112 FAX:03-3608-6697

• **For comprehensive inquiry, consult with**

SII Components Sales Dept.

TEL:043-211-1192 (Direct) FAX:043-211-8032

■ Dimensions





Figure 20 Dimensions

■ Marking



- (0):[A]Fixed
 (1):[T]Fixed
 (2):Year of assembly (last digit)
 (3):Month of assembly (1 to 9,X,Y,Z)
 (4) to (9):Product Series Name

Figure 21 Marking

■ Taping

1. Tape specifications




Figure 22 Tape Specifications

2. Reel specifications

1 reel holds 2000 ICs.


















Figure 23 Reel Specifications

■ Temperature Characteristics







■ Power Supply Dependency Characteristics









■ Transitory Response Characteristics





1. Powering On ($V_{IN}: 0V \rightarrow 5.0V$)

S-8330A30 (Light Load : $I_{OUT}=1mA$) $V_{OUT}=18V$ S-8330A30 (Heavy Load : $I_{OUT}=1mA$) $V_{OUT}=18V$ S-8331A30 (Light Load $\rightarrow I_{OUT}=1mA$) $V_{OUT}=18V$ S-8331A30 (Heavy Load $\rightarrow I_{OUT}=20mA$) $V_{OUT}=18V$ 





2. Power Off Pin Response ($V_{on/off}=0 \rightarrow 5.0V$)

S-8330A30 (Light Load : $I_{OUT}=1mA$) $V_{IN}=5V, V_{OUT}=18V$ S-8330A30 (Heavy Load : $I_{OUT}=10mA$) $V_{IN}=5V, V_{OUT}=18V$ S-8331A30 (Light Load $\rightarrow I_{OUT}=1mA$) $V_{IN}=5V, V_{OUT}=18V$ S-8331A30 (Heavy Load $\rightarrow I_{OUT}=20mA$) $V_{IN}=5V, V_{OUT}=18V$ 









3. Load Variations



4. Power Supply Variations



5. Output Voltage Changeover

S-8330A20 ($V_{OUT}: 8V \rightarrow 14V$) $V_{IN}=5V, I_{OUT}=1mA$ S-8330A20 ($V_{OUT}: 14V \rightarrow 8V$) $V_{IN}=5V, I_{OUT}=10mA$ S-8330A30 ($V_{OUT}: 18V \rightarrow 24V$) $V_{IN}=5V, I_{OUT}=1mA$ S-8330A30 ($V_{OUT}: 24V \rightarrow 18V$) $V_{IN}=5V, I_{OUT}=10mA$ S-8331A20 ($V_{OUT}: 8V \rightarrow 14V$) $V_{IN}=5V, I_{OUT}=1mA$ S-8331A20 ($V_{OUT}: 14V \rightarrow 8V$) $V_{IN}=5V, I_{OUT}=20mA$ S-8331A30 ($V_{OUT}: 18V \rightarrow 24V$) $V_{IN}=5V, I_{OUT}=1mA$ S-8331A30 ($V_{OUT}: 24V \rightarrow 18V$) $V_{IN}=5V, I_{OUT}=20mA$ 

■ Reference Data

The reference data is used to properly determine the best external parts. Tables 1 and 2 list characteristic data of parts recommended to respond to the wide variety of applications.


Table 1 Recommended Parts 1

No.	Product	V _{OUT}	L model	Value L	Diode	C _{OUT}	Remark
(1)	S-8330A20	8V	CD54	47 μ H	MA720	4.7 μ F \times 2	Output current, Efficiency
(2)	S-8330A30	18V	↑	↑	↑	↑	
(3)	↑	30V	↑	↑	↑	↑	
(4)	S-8330A20	8V	LQH4N	↑	↑	↑	
(5)	S-8330A30	18V	↑	↑	↑	↑	
(6)	↑	30V	↑	↑	↑	↑	
(7)	↑	18V	↑	22 μ H	↑	↑	
(8)	↑	↑	↑	100 μ H	↑	↑	Ripple voltage
(9)	S-8330B30	↑	↑	100 μ H	↑	↑	
(10)	S-8330A20	8V	CD54	47 μ H	↑	↑	
(11)	S-8330A30	18V	↑	↑	↑	↑	
(12)	↑	30V	↑	↑	↑	↑	
(13)	S-8330B30	18V	LQH4N	100 μ H	↑	↑	


Table 2 Recommended Parts 2

Part	Product	Manufacturer	Value L	DC resistor	Max. p. c.	Diameter	Height
Inductor	CD54	Sumida Electric	22 μ H	0.18 Ω	1.11A	5.8mm	4.5mm
	↑	↑	47 μ H	0.37 Ω	0.72A	↑	↑
	↑	↑	100 μ H	0.70 Ω	0.52A	↑	↑
	LQH4N	Murata Mfg.	22 μ H	0.94 Ω	0.32A	4.5mm	2.6mm
	↑	↑	47 μ H	1.5 Ω	0.22A	↑	↑
	↑	↑	100 μ H	2.5 Ω	0.16A	↑	↑
	↑	↑	220 μ H	5.4 Ω	0.11A	↑	↑
Diode	MA720	Matsushita	Forward current 500 mA (VF=0.55 V)				
Output capacitor	F93	Nichicon					
External transistor	2SD1624	Sanyo Electric					


(1) S-8330A20 (CD54:47 μ H)
Output Current — Output Voltage Characteristics (Output Current Increase)




S-8330A20 (CD54:47 μ H)
Output Current — Efficiency Characteristics (Output Current Increase)




(2) S-8330A30 (CD54:47 μ H)
Output Current — Output Voltage Characteristics (Output Current Increase)




S-8330A30 (CD54:47 μ H)
Output Current — Efficiency Characteristics (Output Current Increase)




(3) S-8330A30 (CD54:47 μ H)
Output Current — Output Voltage Characteristics (Output Current Increase)




S-8330A30 (CD54:47 μ H)
Output Current — Efficiency Characteristics (Output Current Increase)



(4) S-8330A20 (LQH4N:47 μ H)
Output Current — Output Voltage Characteristics (Output Current Increase)




S-8330A20 (LQH4N:47 μ H)
Output Current — Efficiency Characteristics (Output Current Increase)




(5) S-8330A30 (LQH4N:47 μ H)

Output Current — Output Voltage Characteristics (Output Current Increase)




S-8330A30 (LQH4N:47 μ H)

Output Current — Efficiency Characteristics (Output Current Increase)




(6) S-8330A30 (LQH4N:47 μ H)

Output Current — Output Voltage Characteristics (Output Current Increase)




S-8330A30 (LQH4N:47 μ H)

Output Current — Efficiency Characteristics (Output Current Increase)




(7) S-8330A30 (LQH4N:22 μ H)

Output Current — Output Voltage Characteristics (Output Current Increase)




S-8330A30 (LQH4N:22 μ H)

Output Current — Efficiency Characteristics (Output Current Increase)




(8) S-8330A30 (LQH4N:100 μ H)

Output Current — Output Voltage Characteristics (Output Current Increase)




S-8330A30 (LQH4N:100 μ H)


Output Current — Efficiency Characteristics (Output Current Increase)




(9) S-8330B30 (LQH4N:100 μ H)




S-8330B30 (LQH4N:100 μ H)




(10) S-8330A20 (CD54:47 μ H)




(11) S-8330A30 (CD54:47 μ H)



(12) S-8330A30 (CD54:47 μ H)





Collection of Product FAQs

Author: Hamaguchi Masanao

Date: 98/11/12 (Thursday) 10:17

<Information level>

A: Public (Printing O.K.)

Index: B: Technical

<Product>

Division name: 01 IC

Category 1: 11 Power Supply

Category 2: 4. Switching Regulators

Cal No.: S-8330/31

Related documents:

Question:

When the electronic volume function is not used, how should the input terminals be connected?

Answer:

When the electronic volume function is not used, connect the electronic input terminals as follows:

- Pull down the VDIN terminal to VSS.
- Pull up the VCLK terminal to VIN.
- Pull up the VSTRB terminal to VIN. (Set the pull-up or pull-down resistance at up to 1 MΩ.)

Under these conditions, the output voltage is fixed at the lowest value for each product (the voltage is fixed to 18 V for S-8330A30FS) and the maximum value of the output voltage is 18 V even for S-8330A30FS, which provides the highest output voltage.

When a voltage higher than 18 V is required, it is necessary to add a voltage build-up circuit using an external resistor. For details, refer to "Power Supply for driving large-scale LCD panels" included in the application circuits on the data sheet for the S-8330/8331 series.

<Remarks>

FAQ No.: 11S833X001

Collection of Product FAQs

Author: Tachibana Midori

Date: 98/11/12 (Thursday) 10:17 (Modified:)

<Information level>

A: Public (Printing O.K.)

Index: B: Technical

<Product>

Division name: 01 IC

Category 1: 11 Power Supply

Category 2: 4. Switching Regulators

Cal No.: S-8330/31

Related documents:

Question:

What is the maximum temperature coefficient of the output voltage?

Answer:

The worst temperature coefficient of the output voltage is as follows:

S-8330 260 ppm/°C

When this value is applied to $V_{OUT}=20\text{ V}$, the temperature coefficient of the output voltage, $\Delta V_{out}/\Delta T_a$ (mV/°C), as defined by the SII specifications, is given as:

S-8330 $\pm 5.2\text{ mV/°C}$. (260 ppm/°C x 20 V)

Please note that this is an actual value and not guaranteed as a specification.

<Remarks>

FAQ No.: 11S833003

Collection of Product FAQs

Author: Tachibana Midori

Date: 98/11/12 (Thursday) 10:17 (Modified:)

<Information level>

A: Public (Printing O.K.)

Index: B: Technical

<Product>

Division name: 01 IC

Category 1: 11 Power Supply

Category 2: 4. Switching Regulators


Cal No.: S-8330/31

Related documents:

Question:

After the output voltage is set using the electronic volume, the output voltage decreases to as low as the lowest value of the setting range. Why does this happen?

Answer:



There may be a problem with the VSTRB, VCLK, or VDATA input signals, or with the interface of the S-8330A/B circuit. When a Lo signal is applied to the evaluation circuit using a switch, as shown in the above figure, if there is noise (a voltage drop) at point A in the evaluation circuit, the voltage change at points C and D is delayed compared with that of point B, due to the 10 kΩ resistance. Consequently, VCLK and VSTRB instantaneously exceed the threshold value (approximately 1.3 V for VSHC1), enabling the circuit to recognize the situation as VCLK= VSTRB=Hi, thereby activating the resetting function (18V). To solve this problem, add a capacitor between points C and B.

<Remarks>

FAQ No.: 11S8330002