

VM  
10LA

## FEATURES

- Advanced GaAs technology
- Inputs from 15 to 1500 mV produce constant output
- Optional Threshold Symmetry adjustment (suffix TO)
- Low noise figure for excellent BER at lowest inputs
- Adjustable output voltage,  $V_{pp}$
- Rise and fall times <30 ps
- Guaranteed EYE and step responses
- Internal DC regulation, protection
- Small package

## APPLICATIONS

- 10 Gb/s receiver electronics for low-cost, high reliability fiber optic communication system
- High speed data links

## 10 Gb/s receiver limiting amplifiers

These rugged, low-cost, high performance receiver amplifiers utilize single-substrate COPLANAR MIC thin-film technology and state-of-art GaAs active devices. Designed for receiver applications, these products produce a "quantized" output, effectively providing the decision circuit for the receiver.

Optional threshold symmetry adjustments allows BER optimization at minimum input level. EYE

diagrams exhibit very large phase and amplitude margin even when the input (usually from a PD/TZ amplifier) is "dirty". The output level is electrically adjustable. Output rise and fall times at nominal 50 mVpp input approach 25 ps.

Pulse parameters such as rise and fall times and EYE opening at 10 Gb/s are guaranteed. Supplied with removable DC shells and SMA-F RF connectors.



## Specifications

Model # VM10LA - xxx*	Vin, p-p mV	Gain dB(1)	Vo, p-p Volts(2)	Tr, Tf pS MAX V1 (3) V2		Idc MAX/TYP mA @+15V
- 145	20-1500	44	1.6 (min.)	38	29	400/320
- 155	10-1500	50	1.6 (min.)	38	29	450/360

\*Add "- TO" suffix to specify threshold adjustment option.

### Notes

- (1) Small-signal gain at 25°C, MIN  
 (2) -3 dB adjustability from Vout MAX, for all input voltages  
 (3) Rise/fall times from 10-90% at MIN. (V1) and MAX. (V2) input level.

### Other Specifications

- Minimum EYE opening 85% at 10 Gbps
- NF < 8 dB
- Crossover asymmetry ±20% MAX
- S11 < -10 dB from 400 kHz to 8 GHz; S22 < -10 dB from 100 kHz to 6 GHz
- Output port is DC blocked to ±10 V. MAX input level 2 Vpp
- DC requirement +15 V (internal regulation)
- Reverse voltage protection 50 V
- Output level control terminal: 0 to +12 V at 5 mA MAX; Vo largest at +12V
- Frequency response from 100 kHz (MAX) to 10 GHz (MIN), saturated

### Mechanical Data

Aluminum 6061-T6, nickle plate. RF (SMA-F) and DC shells. Shell removal exposes .015" diameter pin. Heat removal through case (conduction). Wire harness/connector available.

### Reliability

High reliability screening, visual inspections and other screening per VMI Level III, including centrifuge, burn-in, temperature cycle, seal and final test are optional at extra cost.

### Factory Testing Technique

Pattern generator with 25 ps rise/fall time, 10 Gbs/s (NRZ), fixed 2.0 Vpp output. Variable attenuator. Sampling oscilloscope with 12 GHz bandwidth (29 ps). Input to DUT is (2<sup>31</sup> - 1) word length. Correct observed Tr, Tf for system speed, using sum of squares rule.


### Threshold Adjust Option

Apply +5 to -5 V DC at < 10 mA to "TA" pin to optimize system BER at the lowest input level specified. Polarity depends upon system configuration; improvement of 2-3 orders of magnitude in BER are typical, or about 1.5 dB in input level threshold for specified BER.

## Typical Characteristics


### Typical Output EYES

Input varied from 18 mVpp to 1800 mVpp. Input is  $(2^{31} - 1)$  word, 10 Gb/s. Note large phase margins, typically 60% of bit width. EYE opening near 100% at center of bit; good crossover symmetry over 40 dB input range. Sampling scope 10 S persistence, 12.5 GHz BW.




### BER vs. Threshold Control

Duty cycle: 55%, PRBS word:  $2^{31} - 1$ , Input level: Minimum



## Outline Drawing

Dimensions in inches except where indicated



(1) This is an option. Do not confuse with the standard VM10LA-XXX

(2) Marking may either be ink stamped or applied adhesive.



SDL, Inc.  
80 Rose Orchard Way  
San Jose, CA 95134-1365  
Tel: 408-943-9411  
Fax: 408-943-1430  
E-mail: sales@sdli.com

SDL Veritech, Inc.  
111-B Corporate Boulevard  
South Plainfield, NJ 07080  
Tel: 908-769-0300  
Fax: 908-769-0330  
E-mail: sdli@sdli.com

And for the latest information on all SDL products please visit our web site:

[www.sdli.com](http://www.sdli.com)

All statements, technical information and recommendations related to the products herein are based upon information believed to be reliable or accurate. However, the accuracy or completeness thereof is not guaranteed, and no responsibility is assumed for any inaccuracies. The user assumes all risks and liability whatsoever in connection with the use of a product or its application. SDL reserves the right to change at any time without notice the design, specifications, function, fit or form of its products described herein, including withdraw at any time of a product herein as offered for sale. SDL makes no representations that the products herein are free from any intellectual property claims of others.