

PRELIMINARY

Notice: This is not a final specification.
Some parametric limits are subject to change.

MITSUBISHI SEMICONDUCTOR <GaAs FET>

MGFC40V7177A

7.1~7.7GHz BAND 10W INTERNALLY MATCHED GaAs FET

DESCRIPTION

The MGFC40V7177A is an internally impedance-matched GaAs power FET especially designed for use in 7.1~7.7 GHz band amplifiers. The hermetically sealed metal-ceramic package guarantees high reliability.

FEATURES

- Class A operation
- Internally matched to 50Ω system
- High output power
 $P_{1dB} = 10W$ (TYP) @ 7.1~7.7 GHz
- High power gain
 $G_{LP} = 8 dB$ (TYP) @ 7.1~7.7GHz
- High power added efficiency
 $\eta_{add} = 30\%$ (TYP) @ 7.1~7.7 GHz, P_{1dB}
- Hermetically sealed metal-ceramic package
- Low distortion [Item: -51]
 $IM_3 = -45 dBc$ (TYP) @ $P_o = 29$ (dBm) S.C.L.
- Low thermal resistance $R_{th(ch-c)} \leq 2.8^\circ C/W$

APPLICATION

Item-01: 7.1~7.7 GHz band power amplifier

Item-51: Digital radio communication

QUALITY GRADE

- IG

ABSOLUTE MAXIMUM RATINGS ($T_a = 25^\circ C$)

Symbol	Parameter	Ratings	Unit
V_{GDO}	Gate to drain voltage	-15	V
V_{GSO}	Gate to source voltage	-15	V
I_D	Drain current	6	A
I_{GR}	Reverse gate current	-20	mA
I_{GF}	Forward gate current	42	mA
P_T	Total power dissipation *1	53.5	W
T_{ch}	Channel temperature	175	°C
T_{stg}	Storage temperature	-65 ~ +175	°C


*1: $T_c = 25^\circ C$

ELECTRICAL CHARACTERISTICS ($T_a = 25^\circ C$)

Symbol	Parameter	Test conditions	Limits			Unit
			Min	Typ	Max	
I_{DSS}	Saturated drain current	$V_{DS}=3V$, $V_{GS}=0V$	—	4.5	6	A
g_m	Transconductance	$V_{DS}=3V$, $I_D=2.2A$	—	2	—	S
$V_{GS(off)}$	Gate to source cut-off voltage	$V_{DS}=3V$, $I_D=40mA$	-2	-3	-4	V
P_{1dB}	Output power at 1dB gain compression		39.0	40.0	—	dBm
G_{LP}	Linear power gain		7	8	—	dB
I_D	Drain current	$V_{DS}=10V$, $I_D=2.4A$, $f=7.1~7.7GHz$	—	3.0	—	A
η_{add}	Power added efficiency		—	30	—	%
IM_3	3rd order IM distortion *1		-42	-45	—	dBc
$R_{th(ch-c)}$	Thermal resistance *2	ΔV_f method	—	—	2.8	°C/W

*1: Item-51, 2-tone test $P_o = 29$ dBm Single Carrier Level $f = 7.7GHz$ $\Delta f = 10$ MHz. *2: Channel to case

OUTLINE DRAWING Unit: millimeters (inches)



GF-18

RECOMMENDED BIAS CONDITIONS

- $V_{DS} = 10V$
- $I_D = 2.4A$
- $R_g = 50\Omega$
- Refer to Bias Procedure

PRELIMINARY




Notice: This is not a final specification.
Some parametric limits are subject to change.

MITSUBISHI SEMICONDUCTOR <GaAs FET>

MGFC40V7177A

7.1~7.7GHz BAND 10W INTERNALLY MATCHED GaAs FET

TYPICAL CHARACTERISTICS (Ta=25°C)



S PARAMETERS (Ta=25°C, V_{DS}=10V, I_{DS}=2.4A)

f (GHz)	S Parameters (TYP.)							
	S ₁₁		S ₂₁		S ₁₂		S ₂₂	
	Magn.	Angle (deg.)	Magn.	Angle (deg.)	Magn.	Angle (deg.)	Magn.	Angle (deg.)
7.1	0.40	-170.9	3.16	34.3	0.071	-24.8	0.32	-134.4
7.2	0.41	140.3	3.13	-6.5	0.072	-65.4	0.31	-171.2
7.3	0.40	92.6	3.09	-47.4	0.073	-106.6	0.29	-155.1
7.4	0.39	41.3	3.05	-88.0	0.073	-147.2	0.26	123.6
7.5	0.40	-15.1	3.02	-129.5	0.073	171.2	0.21	95.4
7.6	0.44	-76.5	2.82	-173.5	0.071	127.6	0.14	77.0
7.7	0.45	-90.0	2.63	175.0	0.071	90.0	0.19	60.0

NOV. '97