

- Permits Digital Data Transmission Over Coaxial Cable, Strip Line, or Twisted Pair
- Operates With 50-Ω to 500-Ω Transmission Lines
- TTL Compatible With 5-V Supply
- 2.4-V Output at $I_{OH} = -75$ mA
- Uncommitted Emitter-Follower Output Structure for Party-Line Operation
- IMPACT™ Low-Power Schottky Technology
- Improved Replacement for the SN75121 and Signetics 8T13
- Glitchless Power Up/Power Down
- Short-Circuit Protection
- AND-OR Logic Configuration
- High Speed . . . Maximum Propagation Delay Time of 14 ns at $C_L = 15$ pF

description


The SN75ALS121 dual line driver is designed for digital data transmission over lines having impedances from 50 to 500 Ω. It is compatible with standard TTL logic and supply voltage levels.

The low-impedance emitter-follower outputs drive terminated lines such as coaxial cable, strip line, or twisted pair. Having the outputs uncommitted allows wired-OR logic to be performed in party-line applications. Output short-circuit protection is provided by an internal clamping network that turns on when the output voltage drops below approximately 1.5 V. All inputs are in conventional TTL configuration. Gating can be used during power-up and power-down sequences to ensure that no noise is introduced on the line.

The SN75ALS121 employs the IMPACT™ process to achieve fast switching speeds, low power dissipation, and reduced input current requirements.

The SN75ALS121 is characterized for operation from 0°C to 70°C.

D OR N PACKAGE
(TOP VIEW)



NOT RECOMMENDED FOR NEW DESIGN

FUNCTION TABLE

INPUTS						OUTPUT
A	B	C	D	E	F	Y
H	H	H	H	X	X	H
X	X	X	X	H	H	H
All other input combinations						L

H = high level, L = low level, X = irrelevant

IMPACT is a trademark of Texas Instruments Incorporated.

PRODUCTION DATA information is current as of publication date. Products conform to specifications per the terms of Texas Instruments standard warranty. Production processing does not necessarily include testing of all parameters.




POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

Copyright © 1989, Texas Instruments Incorporated


SN75ALS121 DUAL LINE DRIVER

SLLS030A – D1334, SEPTEMBER 1987 – REVISED AUGUST 1989

logic symbol†




logic diagram (positive logic)



† This symbol is in accordance with ANSI/IEEE Std 91-1984 and IEC Publication 617-12.

schematics of inputs and outputs



absolute maximum ratings over operating free-air temperature range (unless otherwise noted)

Supply voltage, V_{CC} (see Note 1)	6 V
Input voltage	6 V
Output voltage	6 V
Continuous total dissipation at (or below) 25°C free air temperature	See Dissipation Rating Table
Operating free-air temperature range	0°C to 70°C
Storage temperature range	– 65°C to 150°C
Lead temperature 1,6 mm (1/16 inch) from case for 10 seconds	260°C

NOTE 1: All voltage values are with respect to network ground terminal.

DISSIPATION RATING TABLE

PACKAGE	$T_A \leq 25^\circ\text{C}$ POWER RATING	OPERATING FACTOR ABOVE $T_A = 25^\circ\text{C}$	$T_A = 70^\circ\text{C}$ POWER RATING
D	950 mW	7.6 mW/°C	608 mW
N	1150 mW	9.2 mW/°C	736 mW

recommended operating conditions

	MIN	NOM	MAX	UNIT
Supply voltage, V_{CC}	4.75	5	5.25	V
High-level input voltage, V_{IH}	2			V
Low-level input voltage, V_{IL}			0.8	V
High-level output current, I_{OH}			– 75	mA
Operating free-air temperature range, T_A	0		70	°C

electrical characteristics over recommended ranges of supply voltage and operating free-air temperature (unless otherwise noted)

PARAMETER	TEST CONDITIONS	MIN	TYP†	MAX	UNIT
V_{IK} Input clamp voltage	$V_{CC} = 5\text{ V}$, $I_I = -12\text{ mA}$			– 1.5	V
$V_{(BR)I}$ Input breakdown voltage	$V_{CC} = 5\text{ V}$, $I_I = 10\text{ mA}$	5.5			V
V_{OH} High-level output voltage	$V_{IH} = 2\text{ V}$, $I_{OH} = -75\text{ mA}$, See Note 2	2.4	3.2		V
I_{OH} High-level output current	$V_{CC} = 5\text{ V}$, $T_A = 25^\circ\text{C}$, $V_{IH} = 4.5\text{ V}$, See Note 2, $V_{OH} = 2\text{ V}$	– 100	– 200	– 250	mA
I_{OL} Low-level output current	$V_{IL} = 0.8\text{ V}$, $V_{OL} = 0.4\text{ V}$, See Note 2			– 800	μA
$I_{O(off)}$ Off-state output current	$V_{CC} = 3\text{ V}$, $V_O = 3\text{ V}$			500	μA
I_{IH} High-level input current	$V_I = 4.5\text{ V}$			40	μA
I_{IL} Low-level input current	$V_I = 0.4\text{ V}$			– 250	μA
I_{OS} Short-circuit output current	$V_{CC} = 5\text{ V}$		– 5	– 30	mA
I_{CCH} Supply current, outputs high	$V_{CC} = 5.25\text{ V}$, All inputs at 2 V, No load		9	14	mA
I_{CCL} Supply current, outputs low	$V_{CC} = 5.25\text{ V}$, All inputs at 0.8 V, No load		13	30	mA

† All typical values are at $V_{CC} = 5\text{ V}$ and $T_A = 25^\circ\text{C}$.

NOTE 2: The output voltage and current limits are ensured for any appropriate combination of high and low inputs specified by the function table for the desired output.

SN75ALS121

DUAL LINE DRIVER


SLLS030A – D1334, SEPTEMBER 1987 – REVISED AUGUST 1989

switching characteristics over recommended ranges of supply voltage and operating free-air temperature


PARAMETER		TEST CONDITIONS		MIN	TYP	MAX	UNIT
t _{PLH}	Propagation delay time, low-to-high-level output	R _L = 37 Ω, C _L = 15 pF, See Figure 1			6	14	ns
t _{PHL}	Propagation delay time, high-to-low-level output				4	14	ns
t _{PLH}	Propagation delay time, low-to-high-level output	R _L = 37 Ω, C _L = 1000 pF, See Figure 1			18	30	ns
t _{PHL}	Propagation delay time, high-to-low-level output				29	50	ns

† All typical values are at V_{CC} = 5 V and T_A = 25°C.

PARAMETER MEASUREMENT INFORMATION



TEST CIRCUIT



VOLTAGE WAVEFORMS

NOTES: A. The pulse generator has the following characteristics: Z_O = 50 Ω, t_w = 200 ns, duty cycle = 50%.
 B. C_L includes probe and jig capacitance.

Figure 1. Test Circuit and Voltage Waveforms

TYPICAL CHARACTERISTICS




Figure 2

IMPORTANT NOTICE

Texas Instruments (TI) reserves the right to make changes to its products or to discontinue any semiconductor product or service without notice, and advises its customers to obtain the latest version of relevant information to verify, before placing orders, that the information being relied on is current and complete.

TI warrants performance of its semiconductor products and related software to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are utilized to the extent TI deems necessary to support this warranty. Specific testing of all parameters of each device is not necessarily performed, except those mandated by government requirements.

Certain applications using semiconductor products may involve potential risks of death, personal injury, or severe property or environmental damage ("Critical Applications").

TI SEMICONDUCTOR PRODUCTS ARE NOT DESIGNED, INTENDED, AUTHORIZED, OR WARRANTED TO BE SUITABLE FOR USE IN LIFE-SUPPORT APPLICATIONS, DEVICES OR SYSTEMS OR OTHER CRITICAL APPLICATIONS.

Inclusion of TI products in such applications is understood to be fully at the risk of the customer. Use of TI products in such applications requires the written approval of an appropriate TI officer. Questions concerning potential risk applications should be directed to TI through a local SC sales office.

In order to minimize risks associated with the customer's applications, adequate design and operating safeguards should be provided by the customer to minimize inherent or procedural hazards.

TI assumes no liability for applications assistance, customer product design, software performance, or infringement of patents or services described herein. Nor does TI warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right of TI covering or relating to any combination, machine, or process in which such semiconductor products or services might be or are used.