
SCAS008C - JULY 1987 - REVISED APRIL 1996

- Inputs Are TTL-Voltage Compatible
- Center-Pin V<sub>CC</sub> and GND Configurations to Minimize High-Speed Switching Noise
- **EPIC**<sup>™</sup> (Enhanced-Performance Implanted CMOS) 1-µm Process
- 500-mA Typical Latch-Up Immunity at 125°C
- **Package Options Include Plastic** Small-Outline Packages (D), Plastic Shrink Small-Outline Packages (DB), Plastic Thin Shrink Small-Outline Packages (PW), and Standard Plastic 300-mil DIPs (N)



### description


This device contains four independent 2-input OR gates. It performs the Boolean function Y = A + B or  $Y = \overline{\overline{A} \bullet \overline{B}}$  in positive logic.

The 74ACT11032 is characterized for operation from -40°C to 85°C.

#### **FUNCTION TABLE** (each gate)


INP	UTS	OUTPUT
Α	В	Y
Н	Χ	Н
X	Н	Н
L	L	L

## logic symbol†



<sup>†</sup>This symbol is in accordance with ANSI/IEEE Std 91-1984 and IEC Publication 617-12.

### logic diagram (positive logic)





Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

EPIC is a trademark of Texas Instruments Incorporated



SCAS008C - JULY 1987 - REVISED APRIL 1996

## 

Output clamp current,  $I_{OK}$  ( $V_O < 0$  or  $V_O > V_{CC}$ )

Continuous output current,  $I_O$  ( $V_O = 0$  to  $V_{CC}$ )

Continuous current through  $V_{CC}$  or GND

Maximum power dissipation at  $T_A = 55^{\circ}C$  (in still air) (see Note 2): D package

 N package
 1.1 W

 PW package
 0.5 W

 Storage temperature range, T<sub>stg</sub>
 -65°C to 150°C

NOTES: 1. The input and output voltage ratings may be exceeded if the input and output current ratings are observed.

2. The maximum package power dissipation is calculated using a junction temperature of 150°C and a board trace length of 750 mils, except for the N package, which has a trace length of zero.

### recommended operating conditions

		MIN	MAX	UNIT
VCC	Supply voltage	4.5	5.5	V
VIH	High-level input voltage	2		V
VIL	Low-level input voltage		8.0	V
VI	Input voltage	0	Vcc	V
VO	Output voltage	0	VCC	V
IOH	High-level output current		-24	mA
loL	Low-level output current		24	mA
Δt/Δν	Input transition rise or fall rate	0	10	ns/V
TA	Operating free-air temperature	-40	85	°C



<sup>†</sup> Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

SCAS008C - JULY 1987 - REVISED APRIL 1996

# electrical characteristics over recommended operating free-air temperature range (unless otherwise noted)

PARAMETER	TEST CONDITIONS	v <sub>CC</sub>	T <sub>A</sub> = 25°C			MIN	MAX	UNIT
			MIN	TYP	MAX	IVIIIV	WAX	UNII
VOH	I <sub>OH</sub> = -50 μA	4.5 V	4.4			4.4		>
		5.5 V	5.4			5.4		
	I <sub>OH</sub> = -24 mA	4.5 V	3.94			3.8		
		5.5 V	4.94			4.8		
	$I_{OH} = -75 \text{ mA}^{\dagger}$	5.5 V				3.85		
	I <sub>OL</sub> = 50 μA	4.5 V			0.1		0.1	٧
		5.5 V			0.1		0.1	
VOL	I <sub>OL</sub> = 24 mA	4.5 V			0.36		0.44	
		5.5 V			0.36		0.44	
	$I_{OL} = 75 \text{ mA}^{\dagger}$	5.5 V					1.65	
lį	V <sub>I</sub> = V <sub>CC</sub> or GND	5.5 V			±0.1		±1	μΑ
Icc	$V_I = V_{CC}$ or GND, $I_O = 0$	5.5 V			4		40	μΑ
Δl <sub>CC</sub> ‡	One input at 3.4 V, Other inputs at GND or V <sub>CC</sub>	5.5 V			0.9		1	mA
C <sub>i</sub>	$V_I = V_{CC}$ or GND	5 V		3.5				pF

<sup>&</sup>lt;sup>†</sup> Not more than one output should be tested at a time, and the duration of the test should not exceed 10 ms.

# switching characteristics over recommended ranges of supply voltage and free-air temperature (unless otherwise noted) (see Figure 1)

PARAMETER	FROM (INPUT)	TO (OUTPUT)	T <sub>A</sub> = 25°C			MIN	MAX	UNIT
			MIN	TYP	MAX	IVIIIN	WAX	UNIT
<sup>t</sup> PLH	A or B	Y	1.5	6.2	8.1	1.5	9	
<sup>t</sup> PHL			1.5	4.9	7.4	1.5	8	ns


## operating characteristics, $V_{CC} = 5 \text{ V}$ , $T_A = 25^{\circ}\text{C}$

	PARAMETER	TEST CON	TYP	UNIT	
C <sub>pd</sub>	Power dissipation capacitance per gate	$C_L = 50 \text{ pF},$	f = 1 MHz	29	pF



<sup>‡</sup> This is the increase in supply current for each input that is at one of the specified TTL voltage levels rather than 0 V or V<sub>CC</sub>.

### PARAMETER MEASUREMENT INFORMATION



NOTES: A.  $C_L$  includes probe and jig capacitance.

- B. Input pulses are supplied by generators having the following characteristics: PRR  $\leq$  1 MHz,  $Z_O = 50 \Omega$ ,  $t_f = 3 \text{ ns}$ ,  $t_f = 3 \text{ ns}$ .
- C. The outputs are measured one at a time with one input transition per measurement.

Figure 1. Load Circuit and Voltage Waveforms



#### **IMPORTANT NOTICE**

Texas Instruments and its subsidiaries (TI) reserve the right to make changes to their products or to discontinue any product or service without notice, and advise customers to obtain the latest version of relevant information to verify, before placing orders, that information being relied on is current and complete. All products are sold subject to the terms and conditions of sale supplied at the time of order acknowledgement, including those pertaining to warranty, patent infringement, and limitation of liability.

TI warrants performance of its semiconductor products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are utilized to the extent TI deems necessary to support this warranty. Specific testing of all parameters of each device is not necessarily performed, except those mandated by government requirements.

CERTAIN APPLICATIONS USING SEMICONDUCTOR PRODUCTS MAY INVOLVE POTENTIAL RISKS OF DEATH, PERSONAL INJURY, OR SEVERE PROPERTY OR ENVIRONMENTAL DAMAGE ("CRITICAL APPLICATIONS"). TI SEMICONDUCTOR PRODUCTS ARE NOT DESIGNED, AUTHORIZED, OR WARRANTED TO BE SUITABLE FOR USE IN LIFE-SUPPORT DEVICES OR SYSTEMS OR OTHER CRITICAL APPLICATIONS. INCLUSION OF TI PRODUCTS IN SUCH APPLICATIONS IS UNDERSTOOD TO BE FULLY AT THE CUSTOMER'S RISK.

In order to minimize risks associated with the customer's applications, adequate design and operating safeguards must be provided by the customer to minimize inherent or procedural hazards.

TI assumes no liability for applications assistance or customer product design. TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right of TI covering or relating to any combination, machine, or process in which such semiconductor products or services might be or are used. TI's publication of information regarding any third party's products or services does not constitute TI's approval, warranty or endorsement thereof.

Copyright © 1998, Texas Instruments Incorporated