


Three-phase motor pre-driver for LBP **BA6680FS**

● Description

BA6680FS is a three-phase motor pre-driver. PWM driving system is adopted in this IC as well as incorporation of a booster to drive N-channel (upper and lower) MOS FET. Current limit, FG amplifier, FG hysteresis amplifier and charge-pump are incorporated as other functions.

● Dimension (Unit : mm)



● Features

- 1)Three-phase motor pre-driver
- 2)Upper and lower N-channel MOS FET driving
- 3)PWM driving
- 4)Built-in charge-pump circuit
- 5)Built-in FG amplifier and hysteresis amplifier
- 6)Built-in current limit circuit

SSOP-A32

● Applications

Paper feed motor for LBP, Motor for OA appliances

● Absolute Maximum Ratings (Ta=25°C)

Parameter	Symbol	Limits	Unit
Power supply voltage	Vcc	36	V
Power dissipation	Pd	950 *	mW
Operating temperature range	Topr	-10 ~ +75	°C
Storage temperature range	Tstg	-40 ~ +150	°C

*Derating : 7.6mW/°C for operation above Ta=25°C

● Recommended Operating Conditions (Ta=25°C)

Parameter	Symbol	Min.	Typ.	Max.	Unit
Power supply voltage	Vcc	16	—	28	V

●Electrical characteristics (Unless otherwise noted; Ta=25°C, Vcc=25.5V)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Circuit current	I _{CC}	11.7	15.7	19.7	mA	
VREG voltage	V _{REG}	5.4	5.9	6.4	V	I _{VREG} =−1mA
Hall input bias current	I _{HA}	−3.0	−0.7	−	μA	
Hall common-mode input voltage range	V _{HAR}	1.0	−	4.9	V	
Boost voltage	V _G	V _{CC} +6	V _{CC} +7	V _{CC} +8	V	
Upper gate High voltage	V _{HG}	V _{CC} +6	V _{CC} +7	V _{CC} +8	V	
Lower gate High voltage	V _{LG}	9.5	10.5	11.5	V	
Current detection voltage	V _{CL}	0.342	0.380	0.413	V	
FG amplifier open loop gain	G _{VFG}	45	54	−	dB	f=3kHz

● Application Circuit

