

B-13/15-622-TPM3-Sxx-60



Features

- Coaxial Single Mode Single Fiber Package with Optional SC/FC/ST/MU Connector
- Wavelength Tx 1310 nm/Rx 1550 nm
- SONET OC-12 SDH STM-4(5-4.1) Compliant
- Single +3.3V Power Supply
- LVPECL Differential Inputs and Outputs
- Wave Solderable and Aqueous Washable
- Class 1 Laser Int. Safety Standard IEC 825 Compliant
- Uncooled Laser Diode with MQW Structure
- Complies with Telcordia (Bellcore) GR-468-CORE
- Temperature Range: 0 to 70 °C
- Optical Isolation > 30 dB
- Cross Talk < -33 dB
- Optical Return Loss >14 dB

Absolute Maximum Rating

Parameter	Symbol	Min.	Max.	Unit	Note
Power Supply Voltage	V _{cc}	0	3.6	V	
Output Current	I _{out}	0	30	mA	
Soldering Temperature	-	-	260	°C	10 seconds on leads only
Operating Temperature	T _{opr}	0	70	°C	
Storage Temperature	T _{stg}	-40	85	°C	

Recommended Operating Condition

Parameter	Symbol	Min.	Typ.	Max.	Unit
Power Supply Voltage	V _{cc}	3.1	3.3	3.5	V
Operating Temperature	T _{opr}	0	-	70	°C
Data Rate		-	622	-	Mbps

Transmitter Specifications, (0<T_{opr}<70°C, 3.1V<V_{cc}<3.5V)

Parameter	Symbol	Min	Typical	Max	Unit	Notes
Optical						
Optical Transmit Power	P _o	-15	-	-8	dBm	Output power is coupled into a 9/125 μm single mode fiber
Output Center Wavelength	λ	1260	1310	1360	nm	
Output Spectrum Width	Δλ			4	nm	RMS(σ)
Extinction Ratio	ER	8.2	-	-	dB	
Output Eye		Compliant with Bellcore TR-NWT-000253 and ITU recommendation G957				
Optical Rise Time	t _r	-	-	1.2	ns	10% to 90% Values
Optical Fall Time	t _f	-	-	1.2	ns	10% to 90% Values
Optical Isolation		30	-	-	dB	Tx: 1310 nm/ Rx: 1550 nm
Optical Return Loss		14	-	-	dB	
Relative Intensity Noise	RIN	-	-	-120	dB/Hz	
Total Jitter	TJ	-	-	0.55	ns	Measured with 2 ²³ -1 PRBS with 72 ones and 72 zeros.

B-13/15-622-TPM3-Sxx-60

Transmitter Specifications, ($0 < T_{opr} < 70^{\circ}\text{C}$, $3.1\text{V} < V_{CC} < 3.5\text{V}$)

Parameter	Symbol	Min	Typical	Max	Unit	Notes
Electrical						
Power Supply Current	I_{CC}	-	-	140	mA	Maximum current is specified at V_{CC} = Maximum @ maximum temperature
Data Input Current-Low	I_{IL}	-350	-	-	μA	
Data Input Current-High	I_{IH}	-	-	350	μA	
Differential Input Voltage	$V_{IH}-V_{IL}$	300	-	-	mV	
Data Input Voltage-Low	$V_{IL}-V_{CC}$	-2.0	-	-1.58	V	These inputs are compatible with 10K, 10KH and 100K ECL and PECL inputs
Data Input Voltage-High	$V_{IH}-V_{CC}$	-1.1	-	-0.74	V	


Receiver Specifications, ($0 < T_{opr} < 70^{\circ}\text{C}$, $3.1\text{V} < V_{CC} < 3.5\text{V}$)

Parameter	Symbol	Min	Typical	Max	Unit	Notes
Optical						
Sensitivity	-	-	-	-28	dBm	Measured with 2 ²³ -1 PRBS with 72 ones and 72 zeros. (ITU-T recommendation G.958)
Maximum Input Power	P_{in}	-3	-	-	dBm	
Signal Detect-Asserted	P_a	-	-	-28	dBm	Measured on transition: low to high
Signal Detect-Deasserted	P_d	-40	-	-	dBm	Measured on transition: high to low
Signal Detect-Hysteresis		-	3.0	-	dB	
Cross Talk	-	-	-	-33	dB	
Wavelength of Operation		1500	-	1600	nm	


Receiver Specifications, ($0 < T_{opr} < 70^{\circ}\text{C}$, $3.1\text{V} < V_{CC} < 3.5\text{V}$)

Parameter	Symbol	Min	Typical	Max	Unit	Notes
Electrical						
Power Supply Current	I_{CC}	-	-	100	mA	The current excludes the output load current
Data Output Voltage-Low	$V_{OL}-V_{CC}$	-1.9	-	-1.6	V	These outputs are compatible with 10K, 10KH and 100KECL and LVPECL outputs.
Data Output Voltage-High	$V_{OH}-V_{CC}$	-1.1	-	-0.8	V	
Signal Detect Output Voltage-Low	$V_{SDL}-V_{CC}$	-1.9	-	-1.6	V	
Signal Detect Output Voltage-High	$V_{SDH}-V_{CC}$	-1.1	-	-0.8	V	

Connection Diagram



PIN	Symbol	Notes
1	RxGND	Directly connect this pin to the receiver ground plane
2	RD+	See recommended circuit schematic
3	RD-	See recommended circuit schematic
4	SD	Active high on this indicates a received optical signal
5	RxVcc	+3.3V dc power for the receiver section
6	TxVcc	+3.3V dc power for the transmitter section
7	TD-	See recommended circuit schematic
8	TD+	See recommended circuit schematic
9	TxGND	Directly connect this pin to the transmitter ground plane



Package Diagram

Diplexer Transceiver Assembly



Ordering Information

B -13/15 - 622 -TPM3 - S SC (FC/ST/MU) - 60

• Tx Wavelength = 1310 nm
Rx Wavelength = 1550 nm

• Communication protocol
(622 Mbps)

• +3.3V Pigtailed Transceiver

• Single mode fiber

• Connector options

• Intermediate Reach

Warnings

Handling Precautions: This device is susceptible to damage as a result of electrostatic discharge (ESD). A static free environment is highly recommended. Follow guidelines according to proper ESD procedures.

Laser Safety: Radiation emitted by laser devices can be dangerous to human eyes. Avoid eye exposure to direct or indirect radiation.

Legal Notice

IMPORTANT NOTICE!

All information contained in this document is subject to change without notice, at Luminent's sole and absolute discretion. Luminent warrants performance of its products to current specifications only in accordance with the company's standard one-year warranty; however, specifications designated as "preliminary" are given to describe components only, and Luminent expressly disclaims any and all warranties for said products, including express, implied, and statutory warranties, warranties of merchantability, fitness for a particular purpose, and non-infringement of proprietary rights. Please refer to the company's Terms and Conditions of Sale for further warranty information.

Luminent assumes no liability for applications assistance, customer product design, software performance, or infringement of patents, services, or intellectual property described herein. No license, either express or implied, is granted under any patent right, copyright, or intellectual property right, and Luminent makes no representations or warranties that the product(s) described herein are free from patent, copyright, or intellectual property rights. Products described in this document are NOT intended for use in implantation or other life support applications where malfunction may result in injury or death to persons. Luminent customers using or selling products for use in such applications do so at their own risk and agree to fully defend and indemnify Luminent for any damages resulting from such use or sale.

THE INFORMATION CONTAINED IN THIS DOCUMENT IS PROVIDED ON AN "AS IS" BASIS. Customer agrees that Luminent is not liable for any actual, consequential, exemplary, or other damages arising directly or indirectly from any use of the information contained in this document. Customer must contact Luminent to obtain the latest version of this publication to verify, before placing any order, that the information contained herein is current.

© Luminent, Inc. 2003
All rights reserved