



Inductive sensor

Bi1,5-EG08K-Y1-H1341



- threaded barrel, M8 x 1
- short version
- stainless steel, 1.4301
- 2-wire DC, nom. 8.2 VDC
- output according to DIN EN 60947-5-6 (NAMUR)
- connector M12 x 1

Wiring diagram



Function principles

Inductive proximity switches are designed for wear-free non-contact detection of metal objects. For this they use a high-frequency electro-magnetic AC field that interacts with the target. With inductive sensors, this field is generated by an LC resonant circuit with a ferrite core coil.

Type	Bi1,5-EG08K-Y1-H1341
Ident-No.	1003620
Rated operating distance S_n	1,5 mm
Mounting mode	flush
Hysteresis (switching distance)	1... 10 %
Min. repeat accuracy	≤ 2 %
Temperature drift	≤ ± 10 %
Operating temperature	-25 ...+ 70 °C
Voltage	nom. 8,2 VDC
Current consumption (off-state)	≥ 2,1 mA
Current consumption (on-state)	≤ 1,2 mA
Max. switching frequency	≤ 5 kHz
Output function	2-wire, NAMUR
Approval according to	KEMA 02 ATEX 1090X
Internal inductivity (L_i) / capacitance (C_i)	150 nF / 150 μH
Marking of device	II 2 G EEx ia IIC T6 (max. U_i = 15 V, I_i = 60 mA, P_i = 130 mW)
Housing style	threaded barrel; M8 x 1
Dimensions	39 mm
Housing material	metal, A2 1.4301 (AISI 304)
Active face	plastic, PA12-GF20
Max. fixing torque of coupling nut	10 Nm
Wiring	connector, M12 x 1
Vibration resistance	55 Hz (1 mm)
Shock resistance	30 x g (11 ms)
Degree of protection	IP67

Inductive sensor


Bi1,5-EG08K-Y1-H1341

Mounting instructions

	minimum gap
Gap D	2 x B
Gap W	3 x Sn
Gap T	3 x B
Gap S	1,5 x B
Gap G	6 x Sn

Diameter of active face B



Ø 8 mm



Inductive sensor

Bi1,5-EG08K-Y1-H1341

Accessories

Typ	Ident-No.	Description	Dimension drawing
BST-08B	6947210	fixing clamp with dead-stop; material: PA6	  
QM-08	6945100	quick-mount fixing clamp with dead-stop; material: chrome-plated brass external thread M12 x 1	
IM1-22EX-R/24VDC	7541210	Isolating switching amplifier, two channels; input for NAMUR signals; optional wire-break and short-circuit monitoring function; selectable normally open or normally closed performance; removeable terminal blocks; 18 mm wide; supply voltage 24 VDC; further isolating switching amplifiers in our "Interface Technology" catalogue.	