



Inductive sensor

Bi5-Q08-AD4X-V1130



- rectangular, height 8mm
- top active face
- metal, GD-Zn
- connector with snap-lock
- 2-wire DC, 10...65 VDC
- normally open
- connector M8 x 1

Wiring diagram



Function principles

Inductive proximity switches are designed for wear-free non-contact detection of metal objects. For this they use a high-frequency electro-magnetic AC field that interacts with the target. With inductive sensors, this field is generated by an LC resonant circuit with a ferrite core coil.

Type	Bi5-Q08-AD4X-V1130
Ident-No.	4414551
Rated operating distance S_n	5 mm
Mounting mode	flush
Hysteresis (switching distance)	1... 15 %
Min. repeat accuracy	≤ 2 %
Temperature drift	$\leq \pm 10$ %
Operating temperature	-25 ... + 70 °C
Rated operational voltage (DC) U_B	10... 65 VDC
Max. ripple	≤ 10 % U_{pp}
Rated operational current (DC) I_e	≤ 100 mA
Max. OFF-state current	$\leq 0,6$ mA
Max. switching frequency	≤ 1 kHz
Rated insulation voltage	$\leq 0,5$ kV
Short-circuit protection	yes, cyclic
Max. voltage drop at I_e	≤ 5 V
Min. operational current I_m	≥ 3 mA
Housing style	rectangular; Q08
Dimensions	32 x 20 x 8 mm
Housing material	metal, GD-Zn
Active face	plastic, PA12-GF30
Wiring	connector, M8 x 1
Vibration resistance	55 Hz (1 mm)
Shock resistance	30 x g (11 ms)
Degree of protection	IP67
Switching status indication	LED yellow

Inductive sensor

Bi5-Q08-AD4X-V1130

Mounting instructions

	minimum gap
Gap D	2 x B
Gap W	3 x Sn
Gap S	1 x B
Gap G	6 x Sn

Width of active face B

20 mm

