



Inductive sensor

Ni4U-EH6,5-AN6X-V1131



- smooth barrel, 6,5 mm diameter
- stainless steel, 1.4301
- factor 1 for all metals
- degree of protection IP68
- magnetic field immune
- extended temperature range
- high switching frequency
- 3-wire DC, 10...30 VDC
- normally open npn output
- connector, M8 x 1

Wiring diagram



Function principles

Inductive proximity switches are designed for wear-free non-contact detection of metal objects. Due to a ferrite-less 3-coil system, Uprox factor 1 sensor have distinct advantages. The detect all metals at the same switching distance, are magnetic field immune and feature large switching distances.

Type	Ni4U-EH6,5-AN6X-V1131
Ident-No.	4600683
Rated operating distance S_n	4 mm
Mounting mode	non-flush
Hysteresis (switching distance)	3... 15 %
Min. repeat accuracy	≤ 2 %
Temperature drift	≤ ± 10 %
Operating temperature	≤ ± 15 %, ≤ -25 °C v ≥ +70 °C -30 ...+ 85 °C
Rated operational voltage (DC) U_B	10... 30 VDC
Max. ripple	≤ 10 % U_{pp}
Rated operational current (DC) I_e	≤ 150 mA
No-load current I_0	≤ 15 mA
Max. OFF-state current	≤ 0,1 mA
Max. switching frequency	≤ 2 kHz
Rated insulation voltage	≤ 0,5 kV
Output function	3-wire, normally open, NPN
Short-circuit protection	yes, cyclic
Max. voltage drop at I_e	≤ 1,8 V
Wire breakage / reverse polarity protection	yes / complete
Protection class	2
Housing style	smooth barrel; 6,5 mm
Dimensions	49 mm
Housing material	metal, A2 1.4301 (AISI 304)
Active face	plastic, PA12-GF20
Wiring	connector, M8 x 1
Vibration resistance	55 Hz (1 mm)
Shock resistance	30 x g (11 ms)
Degree of protection	IP68
Switching status indication	LED yellow

Inductive sensor**Ni4U-EH6,5-AN6X-V1131****Mounting instructions**

Mounting instructions	minimum gap
Gap W	3 x Sn
Gap T	3 x B
Gap S	1,5 x B
Gap G	6 x Sn
Gap N	2 x Sn

Diameter of active face B

Ø 6,5 mm

