



ELECTRONICS, INC.
 44 FARRAND STREET
 BLOOMFIELD, NJ 07003
 (973) 748-5089

NTE5312 thru NTE5317 Single Phase Bridge Rectifier 8 Amp

Features:

- Low Forward Voltage Drop
- Surge Overload Rating: 200A (Peak)
- Mounting Hole Thru for #6 Screw

Maximum Ratings and Electrical Characteristics: ($T_A = +25^\circ\text{C}$ unless otherwise specified. Single Phase, Full Wave, 60Hz, Resistive or Inductive Load. For Capacitive Load, Derate Current by 20%)

| | |
|---|------------|
| Maximum Recurrent Peak Reverse Voltage, P_{RV} | |
| NTE5312 | 100V |
| NTE5313 | 200V |
| NTE5314 | 400V |
| NTE5315 | 600V |
| NTE5316 | 800V |
| NTE5317 | 1000V |
| Maximum RMS Bridge Input Voltage, | |
| NTE5312 | 70V |
| NTE5313 | 140V |
| NTE5314 | 280V |
| NTE5315 | 420V |
| NTE5316 | 560V |
| NTE5317 | 700V |
| Maximum DC Blocking Voltage, | |
| NTE5312 | 100V |
| NTE5313 | 200V |
| NTE5314 | 400V |
| NTE5315 | 600V |
| NTE5316 | 800V |
| NTE5317 | 1000V |
| Maximum Average Forward Output Current ($T_C = +75^\circ\text{C}$), $I_{F(AV)}$ | |
| 8A | |
| Peak Forward Surge Current, I_{FSM} | |
| (8.3ms Single Sine-Wave Superimposed on Rated Load) | |
| 200A | |
| Maximum Forward Voltage Drop (Per Bridge Element, $I_F = 4A$), V_F | |
| 1.1V | |
| Maximum Reverse Current (at Rated DC Blocking Voltage per Element), I_R | |
| $T_A = +25^\circ\text{C}$ | 10 μ A |
| $T_A = +100^\circ\text{C}$ | 1mA |
| Operating Junction Temperature Range, T_J | |
| -55° to +125°C | |
| Storage Temperature Range, T_{stg} | |
| -55° to +150°C | |

