


PT4495—24V

30 Amp "Current Booster" for
PT4472 DC-DC Converter



SLTS095

(Revised 6/30/2000)



Patent pending on package assembly

- 30A Current Boost
(Boosts PT4472 to 60A)
- Tracks V_{out} of PT4472
- Synchronized Operation
- High Efficiency
- Input Voltage: 18V to 36V
- 26-pin Copper Case Package

The PT4495 is a new high-performance 30A "Current Booster" for use with the PT4472 Excalibur™ DC/DC converter. The PT4495 adds a parallel output stage to the PT4472, allowing both to operate in perfect synchronization.

The PT4495 only operates with a PT4472 and is not a stand-alone product. Refer the PT4472 data sheet for the performance specifications. The booster uses the same 26-pin case and has the same package options as its companion converter.

PT Series Suffix (PT1234X)

Case/Pin Configuration

Vertical Through-Hole	N
Horizontal Through-Hole	A
Horizontal Surface Mount	C

Ordering Information


PT4495□

(For dimensions and PC Board layout, see
Package Styles 1200, 1210 and 1215.)

Pin-Out Information

Pin	Function	Pin	Function	Pin	Function
1	$+V_{in}$	10	$+V_{out}$	19	$-V_{out}$
2	$-V_{in}$	11	$+V_{out}$	20	$-V_{sense}$
3	N/C	12	$+V_{out}$	21	N/C
4	V_r	13	$+V_{out}$	22	N/C
5	V_a	14	$-V_{out}$	23	N/C
6	N/C	15	$-V_{out}$	24	N/C
7	N/C	16	$-V_{out}$	25	N/C
8	$+V_{out}$	17	$-V_{out}$	26	DRV
9	$+V_{out}$	18	$-V_{out}$		

Standard Application



Input Capacitors: Although not necessary for stable operation, C_{in} will reduce input ripple. $C_{in} = 33\mu F$ is suggested.

Output Capacitors: A minimum of $330\mu F$ per PT4495 booster module is required for proper operation. Increasing C_{out} will reduce transients due to large and/or fast load steps.

IMPORTANT NOTICE

Texas Instruments and its subsidiaries (TI) reserve the right to make changes to their products or to discontinue any product or service without notice, and advise customers to obtain the latest version of relevant information to verify, before placing orders, that information being relied on is current and complete. All products are sold subject to the terms and conditions of sale supplied at the time of order acknowledgment, including those pertaining to warranty, patent infringement, and limitation of liability.

TI warrants performance of its semiconductor products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are utilized to the extent TI deems necessary to support this warranty. Specific testing of all parameters of each device is not necessarily performed, except those mandated by government requirements.

Customers are responsible for their applications using TI components.

In order to minimize risks associated with the customer's applications, adequate design and operating safeguards must be provided by the customer to minimize inherent or procedural hazards.

TI assumes no liability for applications assistance or customer product design. TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right of TI covering or relating to any combination, machine, or process in which such semiconductor products or services might be or are used. TI's publication of information regarding any third party's products or services does not constitute TI's approval, warranty or endorsement thereof.