



# E1835



Optional Dimming Circuit with Enable

Relative Brightness vs. Input Voltage



Endicott Research Group, Inc.

2601 Wayne St., Endicott NY 13760

607-754-9187 607-754-9255

Made in U.S.A.

page 4.



Endicott Research Group, Inc.

2601 Wayne St., Endicott NY 13760

607-754-9187 Fax 607-754-9255

# E1835

## Specifications and Applications Information

3/27/96

Preliminary

The E1835 (E200II Series) dc to ac inverter is specifically designed to power the Hitachi LMG7550 LCD display to a moderate brightness level from a +5 volt dc source.

The E1835's small size, encapsulated package and low input power requirements (typically 2.4 watts) makes it the ideal power source for battery applications where small size, high efficiency and reliability are critical.


This standard inverter is designed to satisfy the most common cold-cathode lighting requirements for the LMG7550 display. Custom units, providing different inputs, outputs or package refinements are available.

Single Tube  
DC to AC Inverter




E200II Package

Package Configuration



Connection Diagram



\* Input bypass capacitor may be required (10uf - 100uf)

**Absolute Maximum Ratings**

Rating	Symbol	Value	Units
Input Voltage Range	Vin	-0.3 to +6	Vdc
Operating Temperature	To	0 to +70	°C
Storage Temperature	Tstg	-40 to +85	°C

**Recommended Operating Conditions**

Rating	Symbol	Value	Units
Input Voltage	Vin	+2.5 to 5.5	Vdc

**Electrical Characteristics**

Unless otherwise noted Vin = 5.00 Volts dc and Ta = 25°C

Characteristic	Symbol	Min	Typ	Max	Units
Input Current	Iin	-	0.5	0.57	Adc
Operating Frequency	Fo	30	35	40	KHz
Minimum Output Voltage	Vout (min)	1000	-	-	Vrms
Efficiency	η	-	78	-	%
Output Current	Iout	-	4.5	-	marms
Output Voltage (When Powering an Hitachi LMG7550 display)	Vout	-	435	-	Vrms

After tube has been allowed to warm-up for 5 minutes


Specifications subject to change without notice




Endicott Research Group, Inc.

**Typical Performance Curves**


Relative Frequency vs. Input Voltage




Relative Brightness vs. Input Power



Input Power vs. Input Voltage



Input Current vs. Input Voltage



Endicott Research Group, Inc.