

RMLA00400

40 Gb/s Transimpedance Amplifier


ADVANCED INFORMATION

Description

The Raytheon RMLA00400 is a very high speed Transimpedance Amplifier (TIA) MMIC for 40 Gb/s (OC768) fiber optic systems. It is available in die form, and is manufactured using Raytheon's advanced MHEMT process. The TIA is used in conjunction with a photodetector to convert optical signals into a voltage output, or as a general purpose low noise wideband gain stage.

Features

- ◆ MHEMT
- ◆ High bandwidth: 40 GHz
- ◆ Low group delay
- ◆ Low power dissipation: ~450mW.
- ◆ Single ended output
- ◆ DC coupled
- ◆ Effective wideband gain stage
- ◆ Chip size 3.71 mm x 1.70 mm

**Absolute Maximum Ratings¹**

Parameter	Symbol	Value	Unit
Supply Voltage	Vd	+3.5	V
RF Input Power	Pin	-10	dBm
Case Operating Temperature	Tc	-40 to +85	°C
Storage Temperature	Tstg	-40 to +100	°C

Electrical Characteristics^{2,3}

Parameter	Min	Typ	Max	Unit
Frequency Bandwidth (1 dB)		40		GHz
Frequency Bandwidth (3 dB)		45		GHz
Low frequency Cut-off		30		KHz
Gain		16		dB
Gain Flatness		±0.75		dB
Transimpedance		300		Ohms
Group Delay		30		pS p-p
Noise Figure		2.5		dB

Parameter	Min	Typ	Max	Unit
Output Voltage		400		mV p-p
Output Return Loss		15		dB
Quiescent Current		130		mA
Input Noise Current Density		25		pA/√Hz
Vd		3.5		V
Vg1		-3.5		V
Vg2		2.5		V
Case Operating Temp	-40		+85	°C

Notes:

1. No permanent damage with only one parameter set at extreme limit. Other parameters set to typical values.
2. All parameters met at Tc = 25°C, Vd = 3.5V.
3. Measured in a 50 ohm system.

Characteristic performance data and specifications are subject to change without notice.

RMLA00400

40 Gb/s Transimpedance Amplifier

ADVANCED INFORMATION

Figure 1

Functional Block Diagram




Figure 2

Recommended Application Schematic Circuit Diagram





Figure 3

Chip Layout and Bond Pad Locations

(Chip Size=3.710 mm x 1.700 mm x 100 μm Typical, Back of Chip is RF and DC Ground)

Dimensions in mm




Characteristic performance data and specifications are subject to change without notice.

RMLA00400

40 Gb/s Transimpedance Amplifier

ADVANCED INFORMATION

Figure 4
Recommended
Assembly Diagram



**Recommended
Procedure**
for Biasing and
Operation

CAUTION: LOSS OF GATE VOLTAGE (V_{g1}) WHILE DRAIN VOLTAGE (V_d) IS PRESENT MAY DAMAGE THE AMPLIFIER CHIP.

The following sequence of steps must be followed to properly test the amplifier.

Step 1: Turn off RF input power.

Step 2: Connect the DC supply grounds to the grounds of the chip carrier. Apply negative gate 1 bias supply voltage of -5.0 V to V_{g1} .

Step 3: Apply positive bias supply voltage of +3.5 V to V_d , V_{g2} connection.

Step 4: Adjust gate 1 bias voltage V_{g1} to set the quiescent current of $I_{dq} \sim 130$ mA.

Step 5: After the bias condition is established, the RF input signal may now be applied at the appropriate frequency band. Adjust V_{g1} for best gain flatness.

Step 6: Follow turn-off sequence of:

- (i) Turn off RF input power,
- (ii) Turn down and off drain voltage (V_d , V_{g2}),
- (iii) Turn down and off gate bias voltage (V_{g1}).

Characteristic performance data and specifications are subject to change without notice.


RMLA00400

40 Gb/s Transimpedance Amplifier


ADVANCED INFORMATION

Performance Data

Typical Measured Gain Response



Gain & Noise Figure Vs. Frequency
Fixture Measurement





Characteristic performance data and specifications are subject to change without notice.

RMLA00400

40 Gb/s Transimpedance Amplifier

ADVANCED INFORMATION

Performance Data



Characteristic performance data and specifications are subject to change without notice.

Worldwide Sales Representatives

North America

D&L Technical Sales
6139 S. Rural Road, #102
Tempe, AZ 85283
480-730-9553
fax: 480-730-9647
Nicholas Delvecchio, Jr.
dlarizona@aol.com

Hi-Peak Technical Sales
P.O. Box 6067
Amherst, NH 03031
866-230-5453
fax: 603-672-9228
sales@hi-peak.com

Spartech South
2115 Palm Bay Road, NE,
Suite 4
Palm Bay, FL 32904
321-727-8045
fax: 321-727-8086
Jim Morris
jim@spartech-south.com

TEQ Sales, Inc.
920 Davis Road, Suite 304
Elgin, IL 60123
847-742-3767
fax: 847-742-3947
Dennis Culpepper
dculpepper@teqsales.com

Cantec Representatives
8 Strathearn Ave, No. 18
Brampton, Ontario
Canada L6T 4L9
905-791-5922
fax: 905-791-7940
Dave Batten
cantec-ott@cantec-o.net

Steward Technology
6990 Village Pkwy #206
Dublin, CA 94568
925-833-7978
fax: 925-560-6522
John Steward
johnsteward1@msn.com

Europe

Sangus OY
Lunkintie 21,
90460 Oulunsalo
Finland
358-8-8251-100
fax: 358-8-8251-110
Juha Virtala
juha.virtala@sangus.fi

Sangus AB
Berghamnvgen 68
Box 5004
S-165 10 Hasselby
Sweden
Ronny Gustafson
468-0-380210
fax: 468-0-3720954

Globes Elektronik & Co.
Klarastrabe 12
74072 Heilbronn
Germany
49-7131-7810-0
fax: 49-7131-7810-20
Ulrich Blievernicht
hfwelt@globes.de

MTI Engineering Ltd.
Afek Industrial Park
Hamelacha 11
New Industrial Area
Rosh Hayin 48091
Israel
972-3-902-5555
fax: 972-3-902-5556
Adi Peleg
adi_p@mti-group.co.il

Sirces srl
Via C. Boncompagni, 3B
20139 Milano
Italy
3902-57404785
fax: 3902-57409243
Nicola Iacovino
nicola.iacovino@sirces.it

Asia

ITX Corporation
2-5, Kasumigaseki
3-Chome
Chiyoda-Ku
Tokyo 100-6014 Japan
81-3-4288-7073
fax: 81-3-4288-7243
Maekawa Ryosuke
maekawa.ryosuke@
itx-corp.co.jp

Sea Union
9F-1, Building A, No 19-3
San-Chung Road
Nankang Software Park
Taiwan, ROC
Taipei 115
02-2655-3989
fax: 02-2655-3918
Murphy Su
murphy@seaunionweb.com.tw

Worldwide Distribution

Headquarters
Avnet-MCS
6321 San Ignacio Drive
San Jose, CA 95119
408-360-4073
fax: 408-281-8802
Art Herbig
art.herbig@avnet.com

Belgium and Luxembourg
BFI Optilas
Cipalstraat
2440 GEEL
Belgium
32 14 570670
fax: 32 14 570679
sales.be@bfiptilas.avnet.com

United Kingdom
BFI Optilas
Burnt Ash Road
Aylesford, Kent
England
ME207XB
44 1622882467
fax: 44 1622882469
rfsales.uk@
bfiptilas.avnet.com

France
BFI Optilas
4 Allee du Cantal
Evry, Cedex
France
33 16079 5900
fax: 33 16079 8903
sales.fr@
bfiptilas.avnet.com

Holland
BFI Optilas
Chr. Huygensweg 17
2400 AJ ALPHEN AAN DEN
RIJN
The Netherlands
31 172 446060
fax: 33 172 443414
sales.nl@
bfiptilas.avnet.com

Spain
BFI Optilas
C/Isobel Colbrand, 6 - 4a
28050 Madrid
Spain
34 913588611
fax: 34 913589271
sales.es@
bfiptilas.avnet.com

Sales Office Headquarters

**United States
(East Coast)**
Raytheon
362 Lowell Street
Andover, MA 01810
978-684-8628
fax: 978-684-8646
Walter Shelmet
wshelmet@
rrfc.raytheon.com

**United States
(West Coast)**
Raytheon
362 Lowell Street
Andover, MA 01810
978-684-8919
fax: 978-684-8646
Rob Sinclair
robert_w_sinclair@
rrfc.raytheon.com

Europe
Raytheon
AM Teckenberg 53
40883 Ratingen
Germany
49-2102-706-155
fax: 49-2102-706-156
Peter Hales
peter_j_hales@
raytheon.com

Asia
Raytheon
Room 601, Gook Je Ctr. Bldg
191 Hangang Ro 2-GA
Yongsan-Gu, Seoul,
Korea 140-702
82-2-796-5797
fax: 82-2-796-5790
T.G. Lee
tg_lee@
rrfc.raytheon.com

Customer Support

978-684-8900

fax: 978-684-5452

customer_support@rrfc.raytheon.com