


Product Description

Stanford Microdevices' SGA-4286 is a high performance cascadeable 50-ohm amplifier designed for operation at voltages as low as 3.2V. This RFIC uses the latest Silicon Germanium Heterostructure Bipolar Transistor (SiGe HBT) process featuring 1 micron emitters with f_T up to 65 GHz.

This circuit uses a darlington pair topology with resistive feedback for broadband performance as well as stability over its entire temperature range. Internally matched to 50 ohm impedance, the SGA-4286 requires only DC blocking and bypass capacitors for external components.



Preliminary

SGA-4286

DC-3500 MHz Silicon Germanium HBT Cascadeable Gain Block



Product Features

- DC-3500 MHz Operation
- Single Voltage Supply
- Low Current Draw: 45mA at 3.2V typ.
- High Output Intercept: >+29dBm typ. at 850 MHz
- High Power Efficiency: >20%


Applications

- Oscillator Amplifiers
- IF/ RF Buffer Amplifier
- Drivers for CATV Amplifiers
- PA for Low Power Applications


Symbol	Parameters: Test Conditions: $Z_0 = 50 \text{ Ohms}$, $I_d = 45 \text{ ma}$, $T = 25^\circ\text{C}$		Units	Min.	Typ.	Max.
P_{1dB}	Output Power at 1dB Compression	$f = 850 \text{ MHz}$ $f = 1950 \text{ MHz}$	dBm dBm		15.0 12.3	
S_{21}	Small Signal Gain	$f = \text{DC} - 1000 \text{ MHz}$ $f = 1000 - 2000 \text{ MHz}$ $f = 2000 - 3500 \text{ MHz}$	dB dB dB	12.0	13.4 12.0 10.0	
S_{12}	Reverse Isolation	$f = \text{DC} - 1000 \text{ MHz}$ $f = 1000 - 2000 \text{ MHz}$ $f = 2000 - 3500 \text{ MHz}$	dB dB dB		18.6 18.9 18.0	
S_{11}	Input VSWR	$f = \text{DC}-2400 \text{ MHz}$ $f = 2400-3500 \text{ MHz}$	-		1.22:1 1.35:1	
S_{22}	Output VSWR	$f = \text{DC}-2400 \text{ MHz}$ $f = 2400-3500 \text{ MHz}$	-		1.14:1 1.17:1	
IP_3	Third Order Intercept Point	$f = 850 \text{ MHz}$ $f = 1950 \text{ MHz}$	dBm dBm		29.1 26.5	
NF	Noise Figure	$f = 850 \text{ MHz}$ $f = 1950 \text{ MHz}$	dB dB		3.7 4.2	
T_D	Group Delay	$f = 1000 \text{ MHz}$	pS		119.0	
V_D	Device Voltage		V	2.8	3.2	3.6

The information provided herein is believed to be reliable at press time. Stanford Microdevices assumes no responsibility for inaccuracies or omissions. Stanford Microdevices assumes no responsibility for the use of this information, and all such information shall be entirely at the user's own risk. Prices and specifications are subject to change without notice. No patent rights or licenses to any of the circuits described herein are implied or granted to any third party. Stanford Microdevices does not authorize or warrant any Stanford Microdevices product for use in life-support devices and/or systems.
Copyright 1999 Stanford Microdevices, Inc. All worldwide rights reserved.


Parameter	Specification			Unit	Test Condition
	Min	Typ.	Max.		
Device Bias					T= 25C
Operating Voltage		3.2		V	
Operating Current		45.0		mA	
500 MHz					T= 25C
Gain		13.9		dB	
Noise Figure		3.6		dB	
Output IP3		29.4		dBm	
Output P1dB		14.7		dBm	
Input Return Loss		23.8		dB	
Isolation		18.2		dB	
850 MHz					T= 25C
Gain		13.4		dB	
Noise Figure		3.7		dB	
Output IP3		29.1		dBm	
Output P1dB		15.0		dBm	
Input Return Loss		20.7		dB	
Isolation		18.6		dB	
1950 MHz					T= 25C
Gain		12.0		dB	
Noise Figure		4.2		dB	
Output IP3		26.5		dBm	
Output P1dB		12.3		dBm	
Input Return Loss		24.7		dB	
Isolation		18.9		dB	
2400 MHz					T= 25C
Gain		11.1		dB	
Noise Figure		4.3		dB	
Output IP3		25.2		dBm	
Output P1dB		11.0		dBm	
Input Return Loss		20.2		dB	
Isolation		19.4		dB	

Pin #	Function	Description	Device Schematic
1	RF IN	RF input pin. This pin requires the use of an external DC blocking capacitor chosen for the frequency of operation.	
2	GND	Connection to ground. Use via holes for best performance to reduce lead inductance as close to ground leads as possible.	
3	RF OUT/BIAS	RF output and bias pin. DC voltage is present on this pin, therefore a DC blocking capacitor is necessary for proper operation.	
4	GND	Sames as Pin 2	







Application Schematic for +5V Operation at 900 MHz



Application Schematic for +5V Operation at 1900 MHz




The information provided herein is believed to be reliable at press time. Stanford Microdevices assumes no responsibility for inaccuracies or omissions. Stanford Microdevices assumes no responsibility for the use of this information, and all such information shall be entirely at the user's own risk. Prices and specifications are subject to change without notice. No patent rights or licenses to any of the circuits described herein are implied or granted to any third party. Stanford Microdevices does not authorize or warrant any Stanford Microdevices product for use in life-support devices and/or systems.
 Copyright 1999 Stanford Microdevices, Inc. All worldwide rights reserved.




The information provided herein is believed to be reliable at press time. Stanford Microdevices assumes no responsibility for inaccuracies or omissions. Stanford Microdevices assumes no responsibility for the use of this information, and all such information shall be entirely at the user's own risk. Prices and specifications are subject to change without notice. No patent rights or licenses to any of the circuits described herein are implied or granted to any third party. Stanford Microdevices does not authorize or warrant any Stanford Microdevices product for use in life-support devices and/or systems. Copyright 1999 Stanford Microdevices, Inc. All worldwide rights reserved.


S21, Id =45mA, T=-40C




S12, Id =45mA, T=-40C




S11, Id =45mA, T=-40C




S22, Id =45mA, T=-40C



S11, Id=45mA, Ta= -40C




S22, Id=45mA, Ta= -40C




The information provided herein is believed to be reliable at press time. Stanford Microdevices assumes no responsibility for inaccuracies or omissions. Stanford Microdevices assumes no responsibility for the use of this information, and all such information shall be entirely at the user's own risk. Prices and specifications are subject to change without notice. No patent rights or licenses to any of the circuits described herein are implied or granted to any third party. Stanford Microdevices does not authorize or warrant any Stanford Microdevices product for use in life-support devices and/or systems.
 Copyright 1999 Stanford Microdevices, Inc. All worldwide rights reserved.


S21, Id =45mA, T=85C




S12, Id =45mA, T=85C




S11, Id =45mA, T=85C




S22, Id =45mA, T=85C



S11, Id=45mA, Ta= 85C



S22, Id=45mA, Ta= 85C



The information provided herein is believed to be reliable at press time. Stanford Microdevices assumes no responsibility for inaccuracies or omissions. Stanford Microdevices assumes no responsibility for the use of this information, and all such information shall be entirely at the user's own risk. Prices and specifications are subject to change without notice. No patent rights or licenses to any of the circuits described herein are implied or granted to any third party. Stanford Microdevices does not authorize or warrant any Stanford Microdevices product for use in life-support devices and/or systems. Copyright 1999 Stanford Microdevices, Inc. All worldwide rights reserved.

Absolute Maximum Ratings

Parameter	Value	Unit
Supply Current	90	mA
Operating Temperature	-40 to +85	C
Maximum Input Power	+13	dBm
Storage Temperature Range	-40 to +85	C
Operating Junction Temperature	+150	C

Caution:



Operation of this device above any one of these parameters may cause permanent damage. Appropriate precautions in handling, packaging and testing devices must be observed.

Thermal Resistance (Lead-Junction):
97° C/W

Part Number Ordering Information


Part Number	Reel Size	Devices/Reel
SGA-4286-TR1	7"	1000
SGA-4286-TR2	13"	3000

Recommended Bias Resistor Values


Supply Voltage(Vs)	4V	5V	7.5V	9V	12V
Rbias (Ohms)	18	40	96	129	196

Package Dimensions

Pin Designation	
1	RF in
2	GND
3	RF out and Bias
4	GND



PCB Pad Layout



The information provided herein is believed to be reliable at press time. Stanford Microdevices assumes no responsibility for inaccuracies or omissions. Stanford Microdevices assumes no responsibility for the use of this information, and all such information shall be entirely at the user's own risk. Prices and specifications are subject to change without notice. No patent rights or licenses to any of the circuits described herein are implied or granted to any third party. Stanford Microdevices does not authorize or warrant any Stanford Microdevices product for use in life-support devices and/or systems. Copyright 1999 Stanford Microdevices, Inc. All worldwide rights reserved.