Phone: (516) 997-7474 Fax: (516) 997-7479

Website: www.dionics-usa.com

DIH-1378 Power MOSFET SPDT Photovoltaic AC-DC Relay

Features:

- Two AC-DC Relays; One N/C, One N/O
- Easily Connected as Single AC-DC, SPDT Relay
- Fast Switching Speeds, 60 µs Max.
- Low Level Logic Compatibility
- Immune to False Triggering
- Small size, Hermetic 8-pin SIP Package
- High Isolation Voltage
- Designed to Meet MIL-R28750

Applications:

- Replacement of Mechanical Relays
- Motor Control & Power Control
- Aircraft Flight Control Systems
- A.T.E (Automatic Test Equipment)
- Load Control From Processor I/O Ports
- High-side DC Power Switching
- Power Supply Circuits
- Medical Electronics

Description:


The DIH-1378 is a State-of-the-Art Photovoltaic Solid State Relay designed for special AC-DC switching power applications where package space efficiency and high reliability are critical.

Each package contains two independent relays. One is normally closed (N/C) and the other is normally opened (N/O). Both relays are built with separate input LEDs and optically isolated power MOSFET outputs. The N/C and N/O outputs are able to operate either AC or DC. Connecting the two inputs either in series or parallel (depending on available power supply) will convert the (N/C), (N/O) of DIH-1378 from 2 single SPST relays into a single SPDT configuration.

Each relay, A or B, is capable of carrying 150mA AC or DC continuous current and 250mA DC peak current. Each LED optically couples to a Photovoltaic (PV) IC chip which responds by generating a voltage. This voltage is internally connected to the Gate and Source terminals of the output MOSFETs, thus controlling their current. The DIH-1378 is also available screened to military specifications, as required.

Truth Table		
Relay	Input	Output
A	Low	Close
Pins 1-4	High	Open
В	Low	Open
Pins 5-8	High	Close

Pin Designat	tions		
Pin number	Function	Relay	Status
1	Input +		
2	Input -	A	Normally
3	Output	(N/C)	Close
4	Output		
5	Input +		
6	Input -	В	Normally
7	Output	(N/O)	Open
8	Output		




DIH-1378: Power MOSFET SPDT Photovoltaic AC-DC Relay

Electrical Characteristics (@ 25 °C unless otherwise specified):

- ❖ Relay A: Normally Close (N/C)
- Relay B: Normally Open (N/O)

* I	nput Characteristics (Per Relay)				
Symbol	Parameter	Min.	Typ.	Max.	Unit
I_{in}	Input Current	5.0	20.0	30.0	mA
V_{in}	Input Voltage Drop	1.3		1.5	V
$\mathbf{V}_{\mathrm{rev.}}$	Reverse Voltage			10.0	V
$\mathbf{V}_{\mathbf{on}}$	On State Voltage (A)			1.2	V
	On State Voltage (B)	3.5			V
$\mathbf{V}_{ ext{off}}$	OFF State Voltage (A)	3.5			V
	OFF State Voltage (B)			1.2	V




*	Output Characteristics					
Symbol	Parameter	Relay	Тур.	Max.	Unit	Condition
I_{load}	Load Current	A		150 / 250	mA	Continuous / Peak
$\mathbf{R}_{\mathbf{on}}$	On Resistance	A	8	20	W	$I_{in}=20 \text{ (mA)}; V_{op}=80 \text{ (V)}$
		В	8	20	W	$I_{in}=20 \text{ (mA)}; V_{op}=80 \text{ (V)}$
V_{op}	Operating Voltage	A or B	30	80	\mathbf{V}	AC or DC
BV	Breakdown Voltage	A or B		100	\mathbf{V}	DC
T_{on}	Turn-On Time	A	15	60	ms	$V_{in}=3.5V$, P.W* = 100 μ s; $V_{op}=30V$
		В	15	60	ms	$V_{in}=3.5V$, P.W =100 μ s; $V_{op}=30V$
T_{off}	Turn-Off Time	A	40	60	ms	$V_{in}=3.5V$, P.W =100 μ s; $V_{op}=30V$
		В	40	60	ms	$V_{in}=3.5V$, P.W =100 μ s; $V_{op}=30V$
$\mathbf{V_{iso}}$	Input-Output Isolation	A or B	_	400	VDC	

400

PW*: Pulse Width.

Timing Diagram

Maximum Power Dissipation | A or B



Environmental Ratings:

 $\mathbf{m}\mathbf{W}$

- Storage Temperature: -25^oC to +125^oC
- Constant Acceleration: 5000G
- Hermeticity: + Gross 1x10⁻⁵ atm cc/sec + Fine 5 x 10⁻⁸ atm cc/s **
 - ** When screened to MIL-Specs.