



**2.5V/3.3V, High Bandwidth, Hot Insertion,
2-Bit, 2-Port Bus Switch w/ Individual Enables**
Product Features

- Near zero propagation delay
- 5 Ohm switches connect inputs to outputs
- High Bandwidth (>400 MHz)
- Rail-to-Rail, 3.3V or 2.5V Switching
- 5V I/O Tolerant
- 2.5V Supply Voltage Operation
- Permits Hot Insertion
- Packages available:
 - 8-pin 173-mil wide plastic TSSOP (L)
 - 8-pin 118-mil wide plastic MSOP (U)

Applications

- High Bandwidth Data Switching
- Hot Docking

PI3C3305 Logic Block Diagram

PI3C3305 Pin Configuration

Product Pin Description



Pin Name	Description
BE _n	Switch Enable (PI3C3305)
$\overline{B}E_n$	Switch Enable (PI3C3306)
A ₂ -A ₁	Bus A
B ₂ -B ₁	Bus B
V _{CC}	Power
GND	Ground

Product Description

Pericom Semiconductor's PI3C series of logic circuits are produced using the Company's advanced submicron CMOS technology, achieving industry leading speed grades.

The PI3C3305 and PI3C3306 are 2.5V or 3.3 Volt, 2-bit bus switches designed with fast individual enables. When enabled via the associated Bus Enable ($\overline{B}E$) pin, the "A" pin is directly connected to the "B" pin for that particular gate. The bus switch introduces no additional propagation delay or additional ground bounce noise.

The PI3C3306 device has active LOW enables, and the PI3C3305 has active HIGH enables. It is very useful in switching signals that have high bandwidth (>400 MHz).

PI3C3306 Logic Block Diagram

PI3C3306 Pin Configuration

Truth Table⁽¹⁾

PI3C3305 $\overline{B}E_n$	PI3C3306 BE _n	An	Bn	V _{CC}	Function
X	X*	Hi-Z	Hi-Z	GND	Disconnect
L	H	Hi-Z	Hi-Z	V _{CC}	Disconnect
H	L	Bn	An	V _{CC}	Connect

Notes:

1. H = High Voltage Level, L = Low Voltage Level

Hi-Z = High Impedance, X = Don't Care

* A pull-up resistor should be provided for power-up protection.

Maximum Ratings

(Above which the useful life may be impaired. For user guidelines, not tested.)

Storage Temperature.....	-65°C to +150°C
Ambient Temperature with Power Applied	-40°C to +85°C
Supply Voltage to Ground Potential (Inputs & VCC Only)	-0.5V to +4.6V
Supply Voltage to Ground Potential (Outputs & D/O Only)	-0.5V to +4.6V
DC Input Voltage	-0.5V to +5.5V
DC Output Current	120mA
Power Dissipation	0.5W

Note:

Stresses greater than those listed under MAXIMUM RATINGS may cause permanent damage to the device. This is a stress rating only and functional operation of the device at these or any other conditions above those indicated in the operational sections of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect reliability.

DC Electrical Characteristics (Over Operating Range, $T_A = -40^\circ\text{C}$ to $+85^\circ\text{C}$, $V_{CC} = 3.3\text{V} \pm 10\%$)

Parameters	Description	Test Conditions ⁽¹⁾	Min.	Typ. ⁽²⁾	Max.	Units
V_{IH}	Input HIGH Voltage	Guaranteed Logic HIGH Level	2.0		0.8	V
V_{IL}	Input LOW Voltage	Guaranteed Logic LOW Level	-0.5			
I_{IH}	Input HIGH Current	$V_{CC} = \text{Max.}$, $V_{IN} = V_{CC}$		± 1	± 1	μA
I_{IL}	Input LOW Current	$V_{CC} = \text{Max.}$, $V_{IN} = \text{GND}$				
I_{OZH}	High Impedance Output Current	$0 \leq A, B \leq V_{CC}$		± 1	± 1	μA
V_{IK}	Clamp Diode Voltage	$V_{CC} = \text{Min.}$, $I_{IN} = -18\text{mA}$				
R_{ON}	Switch On Resistance ⁽⁴⁾	$V_{CC} = \text{Min.}$, $V_{IN} = 0.0\text{V}$, $I_{ON} = 48\text{mA}$ or 60mA $V_{CC} = \text{Min.}$, $V_{IN} = 2.4\text{V}$, $I_{ON} = 15\text{mA}$	5 8	5 8	7 15	Ohm

Capacitance ($T_A = 25^\circ\text{C}$, $f = 1\text{ MHz}$)

Parameters ⁽⁵⁾	Description	Test Conditions	Typ.	Units
C_{IN}	Input Capacitance	$V_{IN} = 0\text{V}$	3.5	pF
C_{OFF}	A/B Capacitance, Switch Off	$V_{IN} = 0\text{V}$	5.0	pF
C_{ON}	A/B Capacitance, Switch On	$V_{IN} = 0\text{V}$	10.0	pF

Notes:

1. For Max. or Min. conditions, use appropriate value specified under Electrical Characteristics for the applicable device type.
2. Typical values are at $V_{CC} = 3.3\text{V}$, $T_A = 25^\circ\text{C}$ ambient and maximum loading.
3. Not more than one output should be shorted at one time. Duration of the test should not exceed one second.
4. Measured by the voltage drop between A and B pin at indicated current through the switch. ON resistance is determined by the lower of the voltages on the two (A,B) pins.
5. This parameter is determined by device characterization but is not production tested.

Power Supply Characteristics

Parameters	Description	Test Conditions ⁽¹⁾		Min.	Typ. ⁽²⁾	Max.	Units
I _{CC}	Quiescent Power Supply Current	V _{CC} =Max.	V _{IN} =GND or V _{CC}		260	500	μA
ΔI _{CC}	Supply Current per Input HIGH	V _{CC} = Max.	V _{IN} = 3.0V ⁽³⁾			750	

Notes:

1. For Max. or Min. conditions, use appropriate value specified under Electrical Characteristics for the applicable device.
2. Typical values are at V_{CC}=3.3V, +25°C ambient.
3. Per driven input (control input only); A and B pins do not contribute to ΔI_{CC}.

Switching Characteristics over 3.3V Operating Range


Parameters	Description	Conditions ⁽¹⁾	PI3C3305/PI3C3305		Units	
			Com.			
			Min.	Max.		
t _{PLH} t _{PHL}	Propagation Delay ^(2,3) A to B, B to A	C _L = 50 pF, R _L = 500Ω		0.25	ns	
t _{PZH} t _{PZL}	Bus Enable Time		1.5	6.5		
t _{PHZ} t _{PLZ}	Bus Disable Time		1.5	5.5		

Switching Characteristics over 2.5V Operating Range

Parameters	Description	Conditions ⁽¹⁾	PI3C3305/PI3C3306		Units	
			Com.			
			Min.	Max.		
t _{PLH} t _{PHL}	Propagation Delay ^(2,3) A to B, B to A	C _L = 50 pF, R _L = 500Ω		0.25	ns	
t _{PZH} t _{PZL}	Bus Enable Time		1.5	9.8		
t _{PHZ} t _{PLZ}	Bus Disable Time		1.5	8.3		

Notes:

1. See test circuit and waveforms.
2. This parameter is guaranteed but not tested on Propagation Delays.
3. The bus switch contributes no propagational delay other than the RC delay of the ON resistance of the switch and the load capacitance. The time constant for the switch alone is of the order of 0.25ns for 50pF load. Since this time constant is much smaller than the rise/fall times of typical driving signals, it adds very little propagational delay to the system. Propagational delay of the bus switch when used in a system is determined by the driving circuit on the driving side of the switch and its interaction with the load on the driven side.



Output Voltage vs. Input Voltage over Various Supply Voltages

Ordering Information

Part	Pin-Package	Width
PI3C3305L	8-TSSOP (L)	173-mil
PI3C3305U	8-MSOP (U)	118-mil
PI3C3306L	8-TSSOP (L)	173-mil
PI3C3306U	8-MSOP (U)	118-mil

Application Information

Logic Inputs


The logic control inputs can be driven up to +3.6V regardless of the supply voltage. For example, given a +3.3V supply, IN may be driven LOW to 0V and HIGH to 3.6V. Driving IN Rail-to-Rail minimizes power consumption.

Power-Supply Sequencing


Proper power-supply sequencing is advised for all CMOS devices. It is recommended to always apply V_{CC} before applying signals to the input/output or control pins.

Rail-to-Rail is a registered trademark of Nippon Motorola, Ltd

8-Pin TSSOP (L) Package



8-Pin MSOP (U) Package



Notes:

- 1) Controlling Dimensions in Millimeters
- 2) Ref: JEDEC MO-187AA