

## 24-Bit Mux/Demux Bus Switch


### Features

- Near-zero propagation delay
- 5Ω switches connect inputs to outputs
- Direct bus connection when switches are ON
- Internal 500Ω pull-down on A2 ports
- Ultra-low quiescent power (0.2µA typical)
  - Ideally suited for notebook applications
- Industrial operating temperature: -40°C to +85°C
- Make-before-break switching
- Packages available:
  - 56-pin 240-mil wide thin plastic TSSOP (A)
  - 56-pin 300-mil wide plastic SSOP (V)

### Applications

- Memory switching

### Logic Block Diagram



### Truth Table

Function	S0	A1	A2
A1 to B1, A2 to B2	L	B1	B2
A1 to B2, A2 to B1	H	B2	B1

### Note:

1. H = High Voltage Level
- L = Low Voltage Level
- Z = High Impedance

### Description

Pericom Semiconductor's PI5C series of logic circuits are produced using the Company's advanced 0.6 micron CMOS technology.

The PI5C16292 and PI5C162292 are 12-bit to 24-bit Mux/Demux Bus switches designed with a low ON resistance allowing inputs to be connected directly to outputs.

The PI5C162292 device has a built-in 25-ohm series resistor to reduce noise resulting from reflections, thus eliminating the need for an external terminating resistor.

A2 port is not externally connected and, as a result, has an internal 500-ohm pulldown resistor to ground.

### Pin Configuration

S0	1	56	NC
1A1	2	55	NC
NC1	3	54	1B1
2A1	4	53	1B2
NC1	5	52	2B1
3A1	6	51	2B2
NC1	7	50	3B1
GND	8	49	GND
4A1	9	48	3B2
NC1	10	47	4B1
5A1	11	46	4B2
NC1	12	56-Pin	45
6A1	13	A,V	44
NC1	14		43
7A1	15		42
NC1	16		41
VCC	17		40
8A1	18		39
GND	19		38
NC1	20		37
9A1	21		36
NC1	22		35
10A1	23		34
NC1	24		33
11A1	25		32
NC1	26		31
12A1	27		30
NC1	28		29
			12B2

### Product Pin Description

Pin Name	I/O	Description
S0	I	Select Inputs
xA1	I/O	Bus A
xBx	I/O	Bus B
NC		Internally pulled up thru 4.7k resistor
NC1		Leave it unconnected

## Maximum Ratings

(Above which the useful life may be impaired. For user guidelines, not tested.)

Storage Temperature .....	-65°C to +150°C
Ambient Temperature with Power Applied .....	-40°C to +85°C
Supply Voltage to Ground Potential (Inputs & V <sub>CC</sub> Only) .....	-0.5V to +7.0V
Supply Voltage to Ground Potential (Outputs & D/O Only) .....	-0.5V to +7.0V
DC Input Voltage .....	-0.5V to +7.0V
DC Output Current .....	120mA
Power Dissipation .....	1Watt

### Note:

Stresses greater than those listed under MAXIMUM RATINGS may cause permanent damage to the device. This is a stress rating only and functional operation of the device at these or any other conditions above those indicated in the operational sections of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect reliability.

## Recommended Operating Condition

Parameter	Description	Min.	Max.	Units
V <sub>CC</sub>	Supply Voltage	4	5.5	V
V <sub>IH</sub>	High-Level Input Voltage	2	—	V
V <sub>IL</sub>	Low-Level Input Voltage	—	0.8	V
T <sub>A</sub>	Operating Free-Air Temperature	-40	85	°C

## DC Electrical Characteristics (Over the Operating Range, T<sub>A</sub> = -40°C to +85°C, V<sub>CC</sub> = 5V ±10%)

Parameters	Description	Test Conditions <sup>(1)</sup>		Min.	Typ <sup>(2)</sup>	Max.	Units
V <sub>IH</sub>	Input HIGH Voltage	Guaranteed Logic HIGH Level		2.0	—	—	V
V <sub>IL</sub>	Input LOW Voltage	Guaranteed Logic LOW Level		-0.5	—	0.8	V
I <sub>I</sub>	Input Current	V <sub>CC</sub> = Max., V <sub>IN</sub> = V <sub>CC</sub> or GND	—	—	—	±1	μA
		V <sub>CC</sub> = 0, V <sub>IN</sub> = V <sub>CC</sub>	—	—	—	10	μA
V <sub>IK</sub>	Clamp Diode Voltage	V <sub>CC</sub> = Min., I <sub>IN</sub> = -18mA		—	-0.7	-1.2	V
I <sub>OS</sub>	Short Circuit Current <sup>(3)</sup>	A(B) = 0V, B(A) = V <sub>CC</sub>		100	—	—	mA
V <sub>H</sub>	Input Hysteresis at Control Pins	—		—	150	—	mV
r <sub>ON</sub>	Switch On Resistance <sup>(4)</sup>	V <sub>CC</sub> = Min., V <sub>IN</sub> = 0.0V, I <sub>ON</sub> = 64mA	16292	—	5	7	Ω
			162292	20	28	40	Ω
		V <sub>CC</sub> = Min., V <sub>IN</sub> = 2.4V, I <sub>ON</sub> = 15mA	16292	—	—	12	
			162292	20	35	48	

## Capacitance (T<sub>A</sub> = 25°C, f = 1 MHz)

Parameters <sup>(5)</sup>	Description	Test Conditions	Max.	Units
C <sub>IN</sub>	Input Capacitance	V <sub>IN</sub> = 0V	6	pF
C <sub>OFF</sub>	A/B Capacitance, Switch Off	V <sub>IN</sub> = 0V	10	pF
C <sub>ON</sub>	A/B Capacitance, Switch On	V <sub>IN</sub> = 0V	20	pF

### Notes:

- For Max. or Min. conditions, use appropriate value specified under Electrical Characteristics for the applicable device.
- Typical values are at V<sub>CC</sub> = 5.0V, T<sub>A</sub> = 25°C ambient and maximum loading.
- Not more than one output should be shorted at one time. Duration of the test should not exceed one second.
- Measured by the voltage drop between A and B pin at indicated current through the switch. ON resistance is determined by the lower of the voltages on the two (A,B) pins.
- This parameter is determined by device characterization but is not production tested.

## Power Supply Characteristics

Parameters	Description	Test Conditions <sup>(1)</sup>		Min.	Typ <sup>(2)</sup>	Max.	Units	
I <sub>CC</sub>	Quiescent Power Supply Current	V <sub>CC</sub> = MAX.		V <sub>IN</sub> = GND or V <sub>CC</sub>	—	0.1	3.0	μA
ΔI <sub>CC</sub> <sup>(3)</sup>	Supply Current for S0 @ TTL HIGH	V <sub>CC</sub> = MAX.		V <sub>IN</sub> = 3.4 V <sup>(4)</sup> Other Inputs at V <sub>CC</sub> OR GND	—	—	2.5	mA
I <sub>CCD</sub>	Supply Current for S0 per MHz <sup>(5)</sup> Toggling 50% Duty Cycle	V <sub>CC</sub> = Max., A and B Pins Open			—	—	0.75	mA/ MHz

### Notes:

- For conditions shown as Max. or Min., use appropriate value specified under Electrical Characteristics for applicable device.
- Typical values are at V<sub>CC</sub> = 5.0V, +25°C ambient.
- This is the increase in supply current for S0 at the specified TTL voltage level rather than V<sub>CC</sub> or GND.
- Per TTL driven input (V<sub>IN</sub> = 3.4V, S0 only); A and B pins do not contribute to I<sub>CC</sub>.
- This current applies to the control inputs only and represent the current required to switch internal capacitance at the specified frequency. The A and B inputs generate no significant AC or DC currents as they transition. This parameter is not tested, but is guaranteed by design.

## PI5C16292 Switching Characteristics over Operating Range


Parameters	Description	Conditions <sup>(1)</sup>	PI5C16292		Units	
			Com.			
			Min	Max		
t <sub>PLH</sub> t <sub>PHL</sub>	Propagation Delay <sup>(2,3)</sup> xA1 to xBx, xBx to xA1	C <sub>L</sub> = 50pF R <sub>L</sub> = 500Ω R = 500Ω to 7V <sup>(4)</sup>	—	0.25	ns	
t <sub>PZH</sub> t <sub>PZL</sub>	Bus Enable time S to xA1 or xBx		1.5	6.5	ns	
t <sub>PHZ</sub>	Bus Disable time S to xA1 or xBx		1.5	7	ns	
t <sub>PLZ</sub>	S to xA1 or xBx		1.5	8		
t <sub>M</sub>	Make-before-break time <sup>(2)</sup>		0	2	ns	

## PI5C162292 Switching Characteristics over Operating Range

Parameters	Description	Conditions <sup>(1)</sup>	PI5C162292		Units	
			Com.			
			Min	Max		
t <sub>PLH</sub> t <sub>PHL</sub>	Propagation Delay <sup>(2,3)</sup> xA1 to xBx, xBx to xA1	C <sub>L</sub> = 50pF R <sub>L</sub> = 500Ω R = 500Ω to 7V <sup>(4)</sup>	—	1.25	ns	
t <sub>PZH</sub> t <sub>PZL</sub>	Bus Enable Time S to xA1 or xBx		1.5	6.5	ns	
t <sub>PHZ</sub>	Bus Disable Time S to xA1 or xBx		1.5	7	ns	
t <sub>PLZ</sub>	S to xA1 or xBx		1.5	8		
t <sub>M</sub>	Make-before-break time <sup>(2)</sup>		0	2	ns	

### Notes:

- See test circuit and waveforms.
- This parameter is guaranteed but not tested.
- The bus switch contributes no propagational delay other than the RC delay of the ON resistance of the switch and load capacitance. The time constant for the switch alone is of the order of 0.25ns for 50pF load. Since this time constant is much smaller than rise/fall times of typical driving signals, it adds very little propagational delay to the system. Propagational delay of the bus switch, when used in a system, is determined by the driving circuit on the driving side of the switch and its interaction with the load on the driven side.
- Applies to t<sub>PLZ</sub> and t<sub>PZL</sub>.

**56-Pin SSOP (300 Mil Wide) - Package Code: V**

**56-Pin TSSOP (240 Mil Wide) - Package Code: A**
