

TOSHIBA CMOS DIGITAL INTEGRATED CIRCUIT SILICON MONOLITHIC

TC74LVX157F, TC74LVX157FN, TC74LVX157FT**QUAD 2-CHANNEL MULTIPLEXER**

The TC74LVX157 is a high speed CMOS QUAD 2-CHANNEL MULTIPLEXER fabricated with silicon gate C²MOS technology.

Designed for use in 3.3 Volt systems, it achieves high speed operation while maintaining the CMOS low power dissipation. This device is suitable for low voltage and battery operated systems.

This device consist of four 2-input digital multiplexers with common select and strobe inputs.


When the STROBE input is held "H" level, selection of data is inhibited and all the outputs become "L" level.

The SELECT decoding determines whether the A or B inputs get routed to their corresponding Y outputs.

An input protection circuit ensures that 0 to 7V can be applied to the input pins without regard to the supply voltage. This device can be used to interface 5V to 3V systems and two supply systems such as battery back up. This circuit prevents device destruction due to mismatched supply and input voltages.


(Note) The JEDEC SOP (FN) is not available in Japan.

TC74LVX157F




SOP16-P-300-1.27

TC74LVX157FN



SOL16-P-150-1.27

TC74LVX157FT



TSSOP16-P-0044-0.65

Weight

SOP16-P-300-1.27 : 0.18g (Typ.)

SOL16-P-150-1.27 : 0.12g (Typ.)

TSSOP16-P-0044-0.65 : 0.06g (Typ.)


FEATURES

- High speed : $t_{pd} = 5.1\text{ns}$ (Typ.) ($V_{CC} = 3.3\text{V}$)
- Low power dissipation : $I_{CC} = 4\mu\text{A}$ (Max.) ($T_a = 25^\circ\text{C}$)
- Input voltage level : $V_{IL} = 0.8\text{V}$ (Max.) ($V_{CC} = 3\text{V}$)
 $V_{IH} = 2.0\text{V}$ (Min.) ($V_{CC} = 3\text{V}$)
- Power down protection is provided on all inputs.
- Balanced propagation delays : $t_{pLH} \approx t_{pHL}$
- Low noise : $V_{OLP} = 0.5\text{V}$ (Max.)
- Pin and function compatible with 74HC157

● TOSHIBA is continually working to improve the quality and the reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to observe standards of safety, and to avoid situations in which a malfunction or failure of a TOSHIBA product could cause loss of human life, bodily injury or damage to property. In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent products specifications. Also, please keep in mind the precautions and conditions set forth in the TOSHIBA Semiconductor Reliability Handbook.

961001EBA2

PIN ASSIGNMENT




TRUTH TABLE

INPUTS				OUTPUTS
S-bar-T	SELECT	A	B	
H	X	X	X	L
L	L	L	X	L
L	L	H	X	H
L	H	X	L	L
L	H	X	H	H


X : Don't Care

IEC LOGIC SYMBOL



- 961001EBA2'
- The products described in this document are subject to foreign exchange and foreign trade control laws.
 - The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA CORPORATION for any infringements of intellectual property or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any intellectual property or other rights of TOSHIBA CORPORATION or others.
 - The information contained herein is subject to change without notice.

SYSTEM DIAGRAM



MAXIMUM RATINGS

PARAMETER	SYMBOL	RATING	UNIT
Supply Voltage Range	V_{CC}	-0.5~7.0	V
DC Input Voltage	V_{IN}	-0.5~7.0	V
DC Output Voltage	V_{OUT}	-0.5~ V_{CC} + 0.5	V
Input Diode Current	I_{IK}	-20	mA
Output Diode Current	I_{OK}	± 20	mA
DC Output Current	I_{OUT}	± 25	mA
DC V_{CC} / Ground Current	I_{CC}	± 50	mA
Power Dissipation	P_D	180	mW
Storage Temperature	T_{stg}	-65~150	°C

RECOMMENDED OPERATING CONDITIONS

PARAMETER	SYMBOL	RATING	UNIT
Supply Voltage	V_{CC}	2.0~3.6	V
Input Voltage	V_{IN}	0~5.5	V
Output Voltage	V_{OUT}	0~ V_{CC}	V
Operating Temperature	T_{opr}	-40~85	°C
Input Rise And Fall Time	dt/dv	0~100	ns/V

ELECTRICAL CHARACTERISTICS

DC characteristics

PARAMETER		SYM-BOL	TEST CONDITION	V _{CC} (V)	Ta = 25°C			Ta = - 40~85°C		UNIT	
					MIN.	TYP.	MAX.	MIN.	MAX.		
Input Voltage	"H" Level	V _{IH}		2.0	1.5	—	—	1.5	—	V	
				3.0	2.0	—	—	2.0	—		
				3.6	2.4	—	—	2.4	—		
	"L" Level	V _{IL}		2.0	—	—	0.5	—	0.5		
				3.0	—	—	0.8	—	0.8		
				3.6	—	—	0.8	—	0.8		
Output Voltage	"H" Level	V _{OH}	V _{IN} = V _{IH} or V _{IL}	I _{OH} = - 50μA	2.0	1.9	2.0	—	1.9	V	
				I _{OH} = - 50μA	3.0	2.9	3.0	—	2.9		
				I _{OH} = - 4mA	3.0	2.58	—	—	2.48		
	"L" Level	V _{OL}	V _{IN} = V _{IH} or V _{IL}	I _{OL} = 50μA	2.0	—	0.0	0.1	—		
				I _{OL} = 50μA	3.0	—	0.0	0.1	—		
				I _{OL} = 4mA	3.0	—	—	0.36	—		
Input Leakage Current	I _{IN}	V _{IN} = 5.5V or GND		3.6	—	—	± 0.1	—	± 1.0	μA	
Quiescent Supply Current	I _{CC}	V _{IN} = V _{CC} or GND		3.6	—	—	4.0	—	40.0	μA	

AC characteristics (Input $t_r = t_f = 3\text{ns}$)

PARAMETER	SYM-BOL	TEST CONDITION	$T_a = 25^\circ\text{C}$			$T_a = -40\sim85^\circ\text{C}$		UNIT		
			V_{CC} (V)	C_L (pF)	MIN.	TYP.	MAX.			
Propagation Delay Time (A, B-Y)	t_{pLH}		2.7	15	—	6.6	12.5	1.0	15.5	
				50	—	9.1	16.0	1.0	19.0	
	t_{pHL}		3.3 ± 0.3	15	—	5.1	7.9	1.0	9.5	
				50	—	7.6	11.4	1.0	13.0	
Propagation Delay Time (SELECT-Y)	t_{pLH}		2.7	15	—	8.9	16.9	1.0	20.5	
				50	—	11.4	20.4	1.0	24.0	
	t_{pHL}		3.3 ± 0.3	15	—	7.0	11.0	1.0	13.0	
				50	—	9.5	14.5	1.0	16.5	
Propagation Delay Time (\overline{ST} -Y)	t_{pLH}		2.7	15	—	9.1	17.6	1.0	20.5	
				50	—	11.6	21.1	1.0	24.0	
	t_{pHL}		3.3 ± 0.3	15	—	7.2	11.5	1.0	13.5	
				50	—	9.7	15.0	1.0	17.0	
Output To Output Skew	t_{osLH}	(Note 1)	2.7	50	—	—	1.5	—	1.5	
	t_{osHL}		3.3 ± 0.3	50	—	—	1.5	—	1.5	
Input Capacitance	C_{IN}	(Note 2)			—	4	10	—	10	
Power Dissipation Capacitance	C_{PD}	(Note 3)			—	20	—	—	pF	

(Note 1) Parameter guaranteed by design.

$$(t_{osLH} = |t_{pLHm} - t_{pLHn}|, t_{osHL} = |t_{pHLm} - t_{pHLn}|)$$

(Note 2) Parameter guaranteed by design.

(Note 3) C_{PD} is defined as the value of the internal equivalent capacitance which is calculated from the operating current consumption.

Average operating current can be obtained by the equation :

$$I_{CC(\text{opr.})} = C_{PD} \cdot V_{CC} \cdot f_{IN} + I_{CC}/4 \text{ (per bit)}$$


And the total C_{PD} when n pcs. of gate operate can be gained by the following equation :

$$C_{PD} (\text{total}) = 13 + 7 \cdot n$$

Noise characteristics ($T_a = 25^\circ\text{C}$, Input $t_r = t_f = 3\text{ns}$, $C_L = 50\text{pF}$)

PARAMETER	SYMBOL	TEST CONDITION	$V_{CC} (\text{V})$	TYP.	LIMIT	UNIT
			3.3			
Quiet Output Maximum Dynamic V_{OL}	V_{OLP}		3.3	0.3	0.5	V
Quiet Output Minimum Dynamic V_{OL}	V_{OLV}		3.3	-0.3	-0.5	V
Minimum High Level Dynamic Input Voltage	V_{IHD}		3.3	—	2.0	V
Maximum Low Level Dynamic Input Voltage	V_{ILD}		3.3	—	0.8	V


INPUT EQUIVALENT CIRCUIT



OUTLINE DRAWING

SOP16-P-300-1.27

Unit : mm




Weight : 0.18g (Typ.)

OUTLINE DRAWING

SOL16-P-150-1.27

Unit : mm

(Note) This package is not available in Japan.






Weight : 0.12g (Typ.)

OUTLINE DRAWING

TSSOP16-P-0044-0.65

Unit : mm



Weight : 0.06g (Typ.)