COMPLEMENTARY-OUTPUTS HALL-EFFECT LATCH

Type UGN3275K latching Hall-effect sensors are bipolar integrated circuits designed for electronic commutation of brushless dc motors. They feature dual complementary outputs. The latches are typically used to sense matched magnetic flux densities of alternating polarity from multipole ring magnets.

Each sensor IC includes a Hall voltage generator, operational amplifier, Schmitt trigger, voltage regulator, and dual bipolar output transistors. The regulator allows use of the integrated circuit with supply voltages of 4.5 V to 24 V.

If the Hall cell is exposed to a magnetic flux density greater than the operate threshold (B_{OP}), OUTPUT goes low (turns on) and OUTPUT goes high (turns off). The outputs will hold (latch) this state until magnetic field reversal exposes the Hall cell to a magnetic flux density below the release threshold (BRP) when OUTPUT will go high (off) and OUTPUT will go low (on). This state is also latched. Under any condition one output is on while the other is off. Because the operating state switches only with magnetic field reversal, and not merely with a change in the strength, these integrated circuits qualify as true Hall-effect latches.

These complementary-output Hall-effect latches are supplied in a four-pin plastic SIP, 0.200" (5.08 mm) wide, 0.130" (3.3 mm) high, and 0.060" (1.54 mm) thick.

FEATURES

- Operable with Multipole Ring Magnets
- High Reliability
- Small Size
- Output Compatible with All Digital Logic Families
- 4.5 V to 24 V Operation
- High Hysteresis Level Minimizes Stray-Field Problems
- Complementary Outputs

DUTPUT OUTPUT SUPPLY

Dwg. PH-002

Pinning is shown viewed from branded side.


ABSOLUTE MAXIMUM RATINGS


Power Supply, V _{CC} 25 V
Magnetic Flux Density, B Unlimited
Output OFF Voltage, V _{OUT} 25 V
Output ON Current, I _{OUT} 50 mA
Operating Temperature Range,
T _A 20°C to +85°C
Storage Temperature Range,
T _S

Always order by complete part number: | UGN3275K |.



3275 COMPLEMENTARY-OUTPUTS HALL-EFFECT LATCH





ELECTRICAL CHARACTERISTICS at T_A = +25°C, V_{CC} = 4.5 V to 24 V (unless otherwise noted).

Characteristic	Symbol	Test Conditions	Min.	Тур.	Max.	Units
Supply Voltage	V _{CC}	Operating	4.5	_	24	V
Output Saturation Voltage	V _{OUT(SAT)}	$V_{CC} = 4.5 \text{ V}, I_{OUT} = 20 \text{ mA}, B > B_{OP}$	_	_	400	mV
Output Leakage Current	I _{OFF}	$V_{OUT} = 24 \text{ V}, V_{CC} = 24 \text{ V}, B < B_{RP}$	_	_	10	μΑ
Supply Current	I _{cc}	V _{CC} = 24 V, B < B _{RP}	_	_	7.0	mA
Output Rise Time	t _r	$V_{CC} = 12 \text{ V}, R_L = 820 \Omega, C_L = 20 \text{ pF}$	_	0.04	0.4	μs
Output Fall Time	t _f	$V_{CC} = 12 \text{ V}, R_L = 820 \Omega, C_L = 20 \text{ pF}$	_	0.18	0.4	μs


MAGNETIC CHARACTERISTICS

		T _A = 4	-25°C	T _A = -20°C 1		
Characteristic	Symbol	Min.	Max.	Min.	Max.	Units
Operate Point	B _{OP}	25	250	15	250	G
Release Point	B _{RP}	-250	-25	-250	-15	G
Hysteresis	B _{hys}	100	_	100	_	G


NOTES: 1. As used here, negative flux densities are defined as less than zero (algebraic convention).


2. 1 gauss (G) is exactly equal to 0.1 millitesla (mT).





Surface-Mount Lead Form (Suffix -TL)





NOTES: 1. Tolerances on package height and width represent allowable mold offsets. Dimensions given are measured at the widest point (parting line).

- 2. Exact body and lead configuration at vendor's option within limits shown.
- 3. Height does not include mold gate flash.
- 4. Recommended minimum PWB hole diameter to clear transition area is 0.035" (0.89 mm).
- 5. Where no tolerance is specified, dimension is nominal.
- 6. Supplied in bulk pack (500 pieces per bag).

3275 COMPLEMENTARY-OUTPUTS HALL-EFFECT LATCH

HALL-EFFECT SENSORS

		LATCHI	NG HALL-EFFEC	T DIGITA	L SWITCHES	
Partial Part Number	Operate Point (G) Over Oper	Release Point (G) . Voltage & Te	Hysteresis (G) mp. Range	Oper. Temp.	Packages	Replaces and Comments
UGN3175	15 to 180	-180 to -15	>80 (Typ 180)	S	LT, UA	
UGN3177	25 to 150	-150 to -25	>50 (Typ 180)	S	LT, UA	
A3185x	140 to 300	-300 to -140	280 to 600	E/L	LT, UA	
A3187x	50 to 175	-175 to -50	100 to 350	E/L	LT, UA	3077, 3175, 3177
A3188x	80 to 200	-200 to -80	160 to 400	E/L	LT, UA	
A3189x	50 to 250	-250 to -50	100 to 500	E/L	LT, UA	3075, 3076
A3280x	5 to 40	-40 to -5	10 to 80	E/L	LH, LT, UA	chopper stabilized
A3281x	15 to 90	-90 to -15	30 to 180	E/L	LH, LT, UA	chopper stabilized
A3283x	100 to 180	-180 to -100	<400 (Typ 300)	E/L	LH, LT, UA	chopper stabilized
	61	PROTECTED"	LATCHING HALL	-EFFECT	DIGITAL SWIT	CHES
Partial	Operate	Release	Hysteresis			
Part	Point (G)	Point (G)	(G)	Oper.		
Number	Over Oper	. Voltage & Te	mp. Range	Temp.	Packages	Comments
A3195x	40 to 200	-200 to -40	>110 (Typ 220)	E, L	U, LT	active pulldown
A3197x	40 to 200	-200 to -40	>110 (Typ 230)	E, L	U, LT	open-collector output

Notes: 1) Typical data is at $T_A = +25^{\circ}C$ and nominal operating voltage.

2) "x" = Operating Temperature Range [suffix letter or (prefix)]: S (UGN) = -20°C to +85°C, E = -40°C to +85°C, J = -40°C to +115°C, K (UGS) = -40°C to +125°C, L (UGL) = -40°C to +150°C.

The products described herein are manufactured under one or more of the following U.S. patents: 5,045,920; 5,264,783; 5,442,283; 5,389,889; 5,581,179; 5,517,112; 5,619,137; 5,621,319; 5,650,719; 5,686,894; 5,694,038; 5,729,130; 5,917,320; and other patents pending.

Allegro MicroSystems, Inc. reserves the right to make, from time to time, such departures from the detail specifications as may be required to permit improvements in the performance, reliability, or manufacturability of its products. Before placing an order, the user is cautioned to verify that the information being relied upon is current.

Allegro products are not authorized for use as critical components in life-support appliances, devices, or systems without express written approval.

The information included herein is believed to be accurate and reliable. However, Allegro MicroSystems, Inc. assumes no responsibility for its use; nor for any infringements of patents or other rights of third parties that may result from its use.

