MISCELLANEOUS

Amplifer Optic Block
Pigtail Fiber Optic Collimators
Attenuator
VCVOA
Jumper

AMPLIFIER OPTIC BLOCK

•

Features

- Low insertion loss
- High stability and reliability
- Compact size
- Optical path epoxy free

An Optical Block is a basic building unit of an amplifer.


It contains Tap Couplers, Isolators, and Wavelength Division

Multiplexers. The Erbium-Doped Fiber and Gain Flattening Filter
can be assembled into the block per customer's request.


▼ Applications

- Booster amplifier
- Line amplifier
- Preamplifier
- ASE light source

Typical Structure



Ordering Information



PIGTAIL FIBER OPTIC COLLIMATORS

Features

- Compact miniature unit
- Low insertion loss
- High return loss
- Environmental stability and reliability



Applications

- Optical devices
- Fiber optical alignment
- Optical testing systems
- Laser interface




V	

Specifications

CL type	Premium		A Grade
Spectral width (min.) (nm)		60	
Central wavelength (nm)	≥	£1310, 1550, 1310/1550	
Beam diameter (mm)		< 0.5	
Beam divergence (max.) (°)		0.25	
Acceptance angle (max.) (°)		0.15	
Return loss (dB)	65		60
Typ. insertion loss (dB) (any pair)	0.2		0.3
Max. insertion loss (dB)	0.3		0.5
Max. optical power (mW)		300	
Operating temperature (°C)		-20 ∼ +70	
Storage temperature (°C)		-40 ∼ +85	
ensile load (max.) (N) 5			

Ordering Information







ATTENUATOR



▼ Features

- All-fiber construction
- In-line configuration
- Excellent environmental stability and reliability



Applications

- Telecommunication systems
- Digital, hybrid and AM-video systems
- Local area networks
- CATV systems
- Aerospace



Specifications

Туре	Single Window Wideband	Dual Window Wideband	
Attenuation (dB)	3, 5, 10, 15, 20 ± 10%	3, 5, 10, 15, 20 ± 10%	
Operating wavelength (nm)*	1310 ± 40 or 1550 ± 40	1310/1550 ± 40	
Back reflection (dB)		≤ -60	
Operating temperature (°C)	-40 ~ +85		
Storage temperature (°C)	-40 ~ +85		
Fiber type	Corning singlemode SMF-28		
Fiber pigtail type	Bare fiber, 900µm loose tube or 3mm cable		
Fiber pigtail length (m)	1 meter or custom on request		
Package dimensions	Packa	age A, B, C	

^{*} Applications at 980nm and 850nm are available.

VCVOA (VOLTAGE-CONTROLLED VARIABLE OPTICAL ATTENUATOR)

▼ Features

- High reliability
- Latching capability
- Potentiometer feedback to monitor
- Wide attenuation range
- High attenuation resolution
- Mountable on printed circuit board

▼ Applications

- Power equalization in multi-channel optical networks
- Gain-tilt control in optical amplifers
- Balance laser signal into DWDM networks
- Used between stages of EDFA as a constant "gain" block


Specifications			
Specifications	Min.	Typical	Max.
Wavelength range (nm)	1520		1580
Input optical power (mW)			250
Attenuation range (dB)	40		
Attenuation resolution (dB)		0.1	0.15
Residual attenuation (dB)			0.1
Minimum insertion loss (dB)	0.5dB*; 1.2dB**; 1.6dB***		
Temperature dependence of attenuation (dB)			0.2
Wavelength dependence of attenuation (dB)			0.2
Polarization dependent loss (dB)			0.2
Polarization mode dispersion (ps)			0.1
Return loss (dB)			50
Response speed (ms)			100
Repeatability of attenuation setting (dB)			0.15
Backlash in attenuation setting (dB)			0.15
Dimensions (mm)		(L) 25 x (W) 12 x (H) 50	
Operating temperature (°C)	-5		70
Storage temperature (°C)	-5		80

- * With no monitoring tap detector.
- ** With input or output monitoring tap detector.
- *** With input or output monitoring tap detector.


Ordering Information No. of Pigtails 0 = without taps 1 = with input tap only 2 = with input tap only 3 = with input and output taps Package 5 = Standard C = Customer design module Pigtail Type B = 250µm bare fiber L = 900µm loose tube Connector 0 = None 1 = FC/APC 2 = SC/APC 3 = FC/PC 4 = SC/PC 5 = ST/PC 6 = LC/UPC 7 = MU/PC 8 = Customer order 1 = 1m 2 = 2m 3 = Customer specify

JUMPER

Ordering Information



FIBER OPTIC COUPLERS, WDMs, AND ATTENUATORS



Notes